

Product Overview

AR1820HS: 18 MP 1/2.3" CMOS Image Sensor

For complete documentation, see the data sheet

The AR1820HS is an 18 megapixel, 1/2.3-inch format, 1.25 um pixel sensor using ON Semiconductor's A-PixHS™; BSI technology. With a variety of operating modes, the AR1820HS can dynamically optimize resolution, low-light and frame rate for environmental conditions. For example, the camera could run in full 18 megapixel resolution at 24 fps under high-light conditions, and switch to a 2:1 summing and 2:1 binning at 1080p 60 frames-per-second mode for superb low-light performance under darker conditions. With high resolution and frame rates, and a variety of flexible modes, the AR1820HS sensor is excellent for many applications such as surveillance, sports cameras and mobile handsets.

Applications

- Camera
- Security

Part Electrical Specifications

Product	Compliance	Status	Type	Megapixels	Frame Rate (fps)	Optical Format	Shutter Type	Pixel Size (µm)	Output Interface	Color	Package Type
AR1820HSSC00SHEA0-DP1	Pb-free Halide free	Active	CMOS	18.1	24	1/2.3 inch	Electronic Rolling	1.25 x 1.25	MIPI HiSPi™	RGB	IBGA-60
AR1820HSSC00SHEA0-DR	Pb-free Halide free	Active	CMOS	18.1	24		Electronic Rolling	1.25 x 1.25		RGB	IBGA-60
AR1820HSSC12SHEA0-DR	Pb-free Halide free	Active	CMOS	18.1	24	1/2.3 inch	Electronic Rolling	1.25 x 1.25		RGB	IBGA-60
AR1820HSSC12SHEA0-DR1	Pb-free Halide free	Active	CMOS	18.1	24		Electronic Rolling	1.25 x 1.25		RGB	IBGA-60
AR1820HSSC12SMD20	Pb-free Halide free	Active	CMOS	18.1	24	1/2.3 inch	Electronic Rolling	1.25 x 1.25		RGB	
AR1820HSSC31SMD20	Pb-free Halide free	Active	CMOS	18.1	24	1/2.3 inch	Electronic Rolling	1.25 x 1.25		RGB	

For more information please contact your local sales support at www.onsemi.com

Created on: 4/25/2017

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Image Sensors](#) category:

Click to view products by [ON Semiconductor](#) manufacturer:

Other Similar products are found below :

[KAF-16803-ABA-DD-BA](#) [KAI-08051-QBA-JD-BA](#) [AR0330CM1C00SHKA0-CP](#) [KAI-0340-FBA-CB-AA-SINGLE](#) [KAI-08051-ABA-JD-BA](#) [KAI-08051-FBA-JD-BA](#) [KAI-2020-ABA-CP-BA](#) [KAI-01150-FBA-FD-BA](#) [KAI-11002-ABA-CD-B2](#) [AR0331SRSC00SUCA0-DPBR](#) [AR0134CSSM00SUEA0-DRBR](#) [MT9V111IA7ATC-DR](#) [NOIP1SE025KA-GDI](#) [AR0132AT6M00XPEA0-DPBR](#) [MT9V138C12STC-DP1](#) [KAI-08051-AXA-JP-BA](#) [MT9D131C12STC-DR](#) [KAI-04050-FBA-JB-B2](#) [KLI-8023-RAA-ED-AA](#) [MT9V136C12STC-DR1](#) [KAF-0402-ABA-CP-B2](#) [KLI-8023-AAA-ED-AA](#) [KAF-16200-FXA-CD-B2](#) [KAI-04050-AAA-JP-BA](#) [NOM02A4-AG01G](#) [NOM02A4-AR03G](#) [KAF-1603-AAA-CP-B2](#) [TCD1205DG\(8Z,W\)](#) [AR0135CS2M00SUD20](#) [KAF-1001-AAA-CP-B1](#) [KAI-0340-FBA-CB-AA-DUAL](#) [KAF-0402-ABA-CD-B2](#) [KAI-01050-FBA-JD-BA](#) [AR0134CSSC00SUEA0-DRBR](#) [NOIL2SM1300A-GDC](#) [OV02659-A47A](#) [28317](#) [AR0134CSSC00SUEA0-TPBR](#) [NOIP1SE0500A-QDI](#) [AR0330CM1C21SHKA0-CP](#) [AR0135AT2M00XUEA0-DPBR1](#) [KAI-0373-ABA-CB-AE](#) [MT9V034C12STM-DP1](#) [AR0130CSSC00SPBA0-DR1](#) [AR0130CSSM00SPCA0-DRBR1](#) [MT9P031I12STC-DR1](#) [AR0237CSSC00SPRA0-DR](#) [NOIP1SF0480A-SDI-E](#) [MT9V034C12STC-DP1](#) [AR0130CSSC00SPBA0-DP1](#)