

NPN SILICON RF POWER TRANSISTOR

DESCRIPTION:

The **ASI SD1490** is a Common Emitter Device Designed for Class A and AB Amplifier Applications in Television Band IV & V Transmitters.

FEATURES INCLUDE:

- Gold Metalization
- Emitter Ballasting
- Internal Matching

MAXIMUM RATINGS

I_C	8.0 A
V_{CB}	45 V
P_{DISS}	155 W @ T _C = 25 °C
T_J	-55 °C to +200 °C
T_{STG}	-55 °C to +200 °C
q_{JC}	1.15 °C/W

PACKAGE STYLE .450 BAL FLG.(A)

	MINIMUM Inches/mm	MAXIMUM Inches/mm		MINIMUM Inches/mm	MAXIMUM Inches/mm
		055/1.40	K	002/0.05	006/0.15
B	120/3.05	130/3.30	L	055/1.40	065/1.65
C		.785/19.94	M	080/2.03	095/2.41
D	455/11.56	465/11.81	N		195/4.95
E	130/3.30		P	455/11.56	468/11.89
F	230/5.84				
G	128/3.25				
H	838/21.28	850/21.59			
I	1095/27.81	1105/28.07			
J	525/13.34	535/13.59			

1 = Collector 2 = Base
3 = Emitter

CHARACTERISTICS T_C = 25 °C

SYMBOL	TEST CONDITIONS (PER SIDE)	MINIMUM	TYPICAL	MAXIMUM	UNITS
BV_{CEO}	I _C = 200 mA	30			V
BV_{CBO}	I _C = 50 mA	45			V
BV_{EBO}	I _E = 10 mA	3.0			V
h_{FE}	V _{CE} = 5.0 V I _C = 3.0 A	10		100	---
C_{OB}	V _{CB} = 28 V f = 1.0 MHz		72		pF
G_P	V _{CE} = 26.5 V I _C = 2 X 1.6 A f = 860 MHz	8.0	9.0		dB
G_p	V _{CE} = 28 V I _C = 2 X 250 mA f = 860 MHz P _{out} = 50 W	7.0	8.0		dB
IMD₃	V _{CE} = 26.5 V P _{out} = 25 W f = 860 MHz VISION = -8.0dB SOUND = -10 dB CHROMA = -16dB			-45	dBc

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Bipolar Transistors](#) *category:*

Click to view products by [Advanced Semiconductor](#) *manufacturer:*

Other Similar products are found below :

[MAPRST0912-50](#) [MCH4016-TL-H](#) [MMBT5551-G](#) [MRF10120](#) [15GN01CA-TB-E](#) [PH1214-25M](#) [MAPRST0912-350](#) [MMBTH10-TP](#) [BFP640F H6327](#) [BFP 720F H6327](#) [BFP 740F H6327](#) [BFR 360F H6765](#) [MRF10031](#) [NSVF4009SG4T1G](#) [BFP 182R E7764](#)
[BFP405H6740XTSA1](#) [MRF10350](#) [BFR360FH6765XTSA1](#) [BFP410H6327XTSA1](#) [BFP620FH7764XTSA1](#) [BFP720ESDH6327XTSA1](#)
[BFP720FH6327XTSA1](#) [BFR360L3E6765XTMA1](#) [BFP420H6433XTMA1](#) [BFP420H6740XTSA1](#) [BFP420H6801XTSA1](#) [MCH4015-TL-H](#)
[BF888H6327XTSA1](#) [MMBT2222A-G](#) [BFP196WH6327XTSA1](#) [BFP405FH6327XTSA1](#) [BFP640ESDH6327XTSA1](#)
[BFR193L3E6327XTMA1](#) [BFS483H6327XTSA1](#) [NSVF4020SG4T1G](#) [NSVF6003SB6T1G](#) [MRF10005](#) [BFP420FH6327XTSA1](#)
[BFP740FESDH6327XTSA1](#) [BFR181E6327HTSA1](#) [BFR181WH6327XTSA1](#) [BFR182E6327HTSA1](#) [BFR193E6327HTSA1](#)
[BFP181E7764HTSA1](#) [BFP183WH6327XTSA1](#) [BFP720H6327XTSA1](#) [BFR182WH6327XTSA1](#) [BFU590GX](#) [MAPR-000912-500S00](#)
[BFR340FH6327XTSA1](#)