

# ADAM-5056/D/S

# ADAM-5056SO

# ADAM-5057S

16-ch Digital Output Module  
16-ch Source-type Isolated  
Digital Output Module with LED

32-ch Isolated Digital Output Module



## Specifications

### General

- **Certification** CE, FCC class A (ADAM-5056S only)
- **Connectors**
  - ADAM-5056/5056D 1 x Plug-in screw terminal (# 14 ~ 22 AWG)
  - ADAM-5056S 1 x Plug-in screw terminal (# 14 ~ 28 AWG)
- **Enclosure** ABS+PC
- **LED Indicators**
  - ADAM-5056D On: Output logic level 1  
Off: Output logic level 0
  - ADAM-5056S On: Active  
Off: Inactive
- **Power Consumption**
  - ADAM-5056: 0.53 W (max.)
  - ADAM-5056D: 0.84 W (max.)
  - ADAM-5056S: 0.6 W (max.)

### Digital Output

- **Channels** 16
- **Digital Output**
  - ADAM-5056/5056D Open collector to 30 V, 100 mA max. load
  - ADAM-5056S Open collector to 40 V, 200 mA max. load (sink)
- **Operating Voltage** ADAM-5056/5056D: 30 V max
- **Power Dissipation** 300 mW for each channel
- **Protection (Only for ADAM-5056S)**
  - Optical Isolation 2500 V<sub>DC</sub>
  - Overvoltage Protection 70 V<sub>DC</sub>
  - Power Dissipation 300 mW

## Ordering Information

- **ADAM-5056** 16-ch Digital Output Module
- **ADAM-5056D** 16-ch Digital Output Module with LED
- **ADAM-5056S** 16-ch Sink Type Iso. DO Module w/ LED

## Specifications

### General

- **Certification** CE, FCC class A
- **Connectors** 1 x Plug-in screw terminal (# 14 ~ 28 AWG)
- **Enclosure** ABS+PC
- **LED Indicator** On: Active  
Off: Inactive
- **Power Consumption** 0.6 W (Max.)
- **Digital Output**
  - **Channels** 16
  - **Digital Output** 10 ~ 35 V<sub>DC</sub>
  - **Current** 200 mA max. (per channel)  
Channel : 1 W max.
  - **Power Dissipation** Total : 2.2 W

### Protection

- **Optical Isolation** 2,500 V<sub>DC</sub>
- **Overvoltage Protection** 70 V<sub>DC</sub>

## Ordering Information

- **ADAM-5056SO** 16-ch Source Type Iso. DO Module w/ LED

## Specifications

### General

- **Certification** CE, FCC class A
- **Connectors** 1 x 40 pin (wiring line)
- **Enclosure** ABS+PC
- **LED Indicator** On: Active  
Off: Inactive
- **Power Consumption** 1W (Max.)

### Digital Output

- **Channels** 32
- **Digital Output** Must connect with 2 units of ADAM-3920R

### Protection

- **Optical Isolation** 2,500 V<sub>DC</sub>
- **Overvoltage Protection** 70 V<sub>DC</sub>

### Relay Spec. of ADAM-3920R

- **Contact Rating** 10A @ 250 V<sub>AC</sub>  
10A @ 30 V<sub>DC</sub>
- **Contact Resistance** 100 mΩ
- **Operation Time** 15 ms
- **Relay Type SPST** (Form A)
- **Release Time** 5 ms max
- **Life Expectancy** 1.7 x 10<sup>6</sup> at related load
- **Insulation Resistance** 1GΩ @ 500 V<sub>DC</sub>
- **Power Input** +24 V<sub>DC</sub>
- **Mounting** DIN 35 rail, wall, rack (with mounting kit)

**Note:** ADAM-5057S must connect with 2 units of ADAM-3920R via PCL-10220

**Note:** only for ADAM-5550 & 5560 Series

## Ordering Information

- **ADAM-5057S** 32-ch Digital Output Module
- **ADAM-3920R** 20-pin Flat Cable Wiring Relay Board
- **PCL-10220** 40-pin IDC to two 20-pin IDC cable, 1m

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [I/O Modules](#) category:*

*Click to view products by [Advantech](#) manufacturer:*

Other Similar products are found below :

[70L-IDC5S](#) [70L-OAC-L](#) [70Z3289-4](#) [G21960000700](#) [G21960002700](#) [G34960002700](#) [OACU](#) [C4SWOUT](#) [PB16H](#) [G34960001700](#) [G3TA-OA101SZ-1](#) [DC24](#) [G77-S](#) [5607189](#) [DA5](#) [ODC-24A](#) [IDC5P](#) [FC6A-N16B1](#) [6421](#) [70MRCQ32-HL](#) [G3TAOD201SDC24](#) [C200H-LK201-V1](#)  
[G3TA-OA202SZ-US](#) [DC12](#) [GT1-OD16](#) [GT1-AD04CST](#) [B7AM-6BS](#) [70GRCQ24-HS](#) [6422](#) [84110410](#) [GT1-OD16MX](#) [G7VC-OC16-B7](#)  
[70MRCK24-DIN](#) [6202](#) [6402](#) [PI/NI-2D/24](#) [FC6A-J2C1](#) [FC6A-KC1C](#) [FC6A-R081](#) [FC6A-J8CU1](#) [GP32900003700](#) [641-480-5022](#) [PB16H](#)  
[84145010](#) [84110210](#) [FRUSB1601](#) [PCL-720+-BE](#) [FRRJ451601](#) [AP24MX3DB25F](#) [ADAM-5053S-AE](#) [WISE-S614-A](#) [C200H-OD211](#)