

# AIW-166K1

## Intel® Wireless 6E AX210 (No vPro) M.2 2230 A-E Key module with cables and antennas



### Features

- IEEE 802.11 ax/ac/a/b/g/n (2.4GHz/5GHz/6GHz) + Bluetooth 5.2
- 2Tx/2Rx
- WPA2\*, WPA3\*
- 802.1x EAP-TLS, EAP-TTLS/MSCHAV2, PEAPv0-MSCHAPv2 (EAP-SIM, EAP-AKA, EAP-AKA')
- Supports wide operating temperatures (0 ~ 70 °C/32 ~ 158 °F)
- Supports Windows 10\*, Linux\*, and Chrome OS\*
- Wi-Fi 6 technology with 1024QAM and 160Mhz channels

### Introduction

Advantech's AIW-166K1 wireless kit comprises a module, 2 cables, and 2 antennas. It facilitates easy assembly and integration.

### Specifications

Main Chipset	Intel 6E AX210 (No Vpro)
Tx/Rx	2Tx/ 2Rx
IEEE WLAN Standard	IEEE 802.11a, b, d, e, g, h, i, k, n, r, u, v, w, ac, ax
Bluetooth®	Bluetooth® 5.2
Form Factor	M.2 2230, A-E Key card
Interface	Wi-Fi: PCI-E, Bluetooth: USB
Operation Voltage	3.3V
Security	WPA2*, WPA3* Authentication Protocols 802.1x EAP-TLS, EAP-TTLS/MSCHAV2, PEAPv0 -MSCHAPv2 (EAP-SIM, EAP-AKA, EAP-AKA') Encryption 128-bit AES-CCMP, 56-bit AES-GCMP
O.S Supported	Windows 10*, Linux*, Chrome OS*
Operating temperature	0 ~ 70 °C/32 ~ 158 °F
Dimensions (H x W x D)	22 x 30 x 2.4mm / 0.86 x 1.18 x .09 in

### Ordering Information

Part No.	Product Description
AIW-166K1	Intel® Wireless 6E AX210 802.11ax (no Vpro)+ BT 5.2 M.2 2230 A-E Key module with cables and antennas kit

### Packing List

Part	Specifications	Qty
EWM-W165M201E	Intel® Wireless 6E AX210 802.11ax (no Vpro)+ BT 5.2 M.2 2230 module	1
1750007965-01	Wi-Fi Coaxial Cable, SMA (M) to MHF4, 30 cm (.98 in)	2
1751000342-01	2.4GHz+5GHz+6GHz Dipole Antenna	2
1930006770-01	Screw M2.5*4L F/S D=4.5 H=0.8+ST Ni Nk	2

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Multiprotocol Modules](#) category:*

*Click to view products by [Advantech](#) manufacturer:*

Other Similar products are found below :

[9260.NGWG.NV 958867](#) [AX210.NGWG.NV](#) [BM833](#) [ESP32-C3-MINI-1U-H4](#) [ESP32-WROOM-32U-16MB](#) [ESP32-WROOM-32UE](#)  
[ESP32-WROOM-32D-H4](#) [ESP32-WROOM-32U-H4](#) [ESP32-PICO-MINI-02U-N8R2](#) [ESP32-C6-WROOM-1-N4](#) [ESP32-C6-WROOM-1U-N4](#)  
[ESP32-C6-WROOM-1-N8](#) [BE200.NGWG.NV](#) [BE200.NGWG](#) [BE202.NGWG.NV](#) [BE200.NGWG.NVX](#) [AX411.NGWG.NV](#) [AX210.D2WG](#)  
[AX210.NGWG.NVX](#) [AX211.NGWG](#) [EC200UEUAA-N05-TA0AA](#) [SC20ELSATEA-8GB-UGAD](#) [SG560DEUPA-U61-TA0AA](#)  
[AX211.NGWG.NV](#) [ISM43340-M4G-L44-10CF-C6.2.1.11](#) [KG100SABMD](#) [BC40P](#) [S007-PIN254](#) [S007-PIN127](#) [ESP32-C3-12F](#)  
[FC41DAHMD](#) [EWM-W179M201E](#) [ESP32-C6-WROOM-1U-N8](#) [ATWILC3000-MR110CA](#) [RS9113-NBZ-D5W](#) [ATWINC3400-](#)  
[MR210UA122](#) [ESP32-WROOM-32](#) [AMPAK AP12356 WIFI/BT KIT](#) [AIW-154BN](#) [AIW-165BN](#) [AIW-166K1](#) [AIW-166K2](#) [AIW-166K3](#)  
[AIW-166K4](#) [AIW-355 DQ-N01](#) [AIW-355 DQ-C01](#) [EWM-W159M201E](#) [EWM-W192K1](#) [EWM-W192K2](#) [W106C](#)