


# EWM-G110H

## Embedded Multi-GPS/ GNSS + G sensor Module Half-size Mini PCIe Card

**NEW**



### Features

- 72-Ch u-blox NEO-M8 engine (GPS, GLONASS, BeiDou, Galileo, QZSS and SBAS)
- Untethered Dead Reckoning(UDR)
- Including 3D inertial sensors
- 1.5 second TTFF for Hot Starts, Open sky code start 26 second.
- Accuracy SBAS 2.0 m CEP
- Operating temperature: -40 to +85° C

### Specifications

Main Chipset	u-blox NEO-M8U
Receiver Type	72 Channels GPS/QZSS L1 C/A, GLONASS L1 L10F, BeiDou B1, SBAS L1 C/A: WAAS/EGNOS/MSAS, Galileo-ready E1B/C
Time-To-First-Fix (GPS + GLONASS)	Cold Start: 26 s Hot Start: 1.5 s Aiding Start: 2 s
Sensitivity (GPS + GLONASS)	Tracking & Navigation: -167 dBm Reacquisition: -160 dBm Cold Start: -148 dBm
Horizontal Position Accuracy	SBAS: 2.0 m
Accuracy of Time Pulse Signal	RMS: 30 ns 99%: 60 ns Time Pulse Configurable: f=0.25...10M Hz
Velocity Accuracy	0.05 m/s
Heading Accuracy	0.3 degrees
Dynamics	< 4 g
Operational Limits	Altitude: 50000 m, Velocity: 500 m/s
Operating Temperature	-40 to +85° C

### Ordering Information

Part No.	Product Description
EWM-G110H01E	Industrial GPS NEO-M8U, GPS/BeiDou/Galileo/GLONASS + G sensor, Half-size Mini PCIe Card

### Suggested Antenna and Cable

Part No.	Specifications
1750007991-01	GPS antenna 1575 MHz, Antenna 3 dBi, (Zenith) L1: 1575.42 MHz, B2: 1561.098 MHz, GNSS: 1602 MHz antenna 4.94 x 3.93 x 1.49, RHCP and SMA male (cm)
1750006264	Coaxial Cable, 15 cm, SMA (F) to MHF
1750006009	Coaxial Cable, 25 cm, SMA (F) to MHF

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [GPS Modules](#) category:*

*Click to view products by [Advantech](#) manufacturer:*

Other Similar products are found below :

[ISM3333-C6.1](#) [SIM68M](#) [GPS-11858](#) [SL871GPS232R001](#) [DD-14239](#) [M20050-1](#) [M20048-1](#) [NEO-M8M-0](#) [S2-105Y0-Z1E0G](#) [NEO-M8P-0](#)  
[SIM28ML](#) [EWM-G110H01E](#) [WISE-4610P-NA](#) [M10578-A2](#) [M10578-A3](#) [GPS-13740](#) [MIKROE-4150](#) [28504](#) [L26ADR-S89](#) [L26T-S89](#)  
[L70B-M39](#) [L86-M33](#) [L89-S90](#) [L96-M33](#) [S2-10640-Z1G0D](#) [EL.1A](#) [4037735105317](#) [4037735105331](#) [W2SG0084i-B-T](#) [2614021137000](#)  
[TEL0132](#) [PKG300060P](#) [RXM-GPS-F4-T](#) [RXM-GPS-FM-B](#) [A1084-A](#) [A2100-A](#) [L80-M39](#) [GYSFFMAXC](#) [W2SG0008i-B-T](#)