

EWM-W179M2

IEEE 802.11ax/ac/b/g/n + Bluetooth 5.2 M.2 2230 (A/E-Key) Card



Features

- IEEE 802.11 ax/ac/b/g/n + Bluetooth 5.2 HS standard
- 2Tx/ 2Rx
- 64/128 bit WEP, WPA, WPA2, WPA3, 802.1x
- Operating temperature: 0 to 70 °C
- Compatible with Nvidia and NXP platforms
- Multiple certification support

Specifications

Main Chipset	RTL8852BE
Tx/Rx	2Tx/ 2Rx (2 IPEX MHF4 connector Receptacle)
Standard Conformance	Wi-Fi 6 + BT5.2
Form Factor	M.2 2230, A/E-key card
Interface	Wi-Fi: PCI-E, Bluetooth: USB
Operation Voltage	DC 3.0 ~ 3.3V
Power Consumption	TX Mode: 860mA
Security	64/128 bit WEP, WPA, WPA2, WPA3, 802.1x
O.S Supported	Windows/Linux/Android
Temperature Ranges	Operation: 0 to 70 °C
Dimensions (L x W x H)	22 x 30 x 2.2 mm

Ordering Information

Part No.	Product Description
EWM-W179M201E	Advantech Brand, Wi-Fi 6 + BT 5.2, RTL8852BE, 2T2R, M.2 2230 A/E key

Suggested Antenna and Cable

Part No.	Specifications
1751000433-01	Wi-Fi 2.4GHz, 5GHz and 6GHz IP65 dipole Antenna
1751000489-01	Wi-Fi Coaxial IP65 Cable, RP SMA(M) to MFH4, L:250mm
1750007965-01	WiFi Coaxial Cable, SMA (M) to MHF4, L: 300mm
1751000460-01	WiFi Tri band 2.4G, 5G and 6G dipole antenna

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Multiprotocol Modules](#) category:

Click to view products by [Advantech](#) manufacturer:

Other Similar products are found below :

[9260.NGWG.NV 958867](#) [AX210.NGWG.NV](#) [BM833](#) [ESP32-C3-MINI-1U-H4](#) [ESP32-WROOM-32U-16MB](#) [ESP32-WROOM-32UE](#)
[ESP32-WROOM-32D-H4](#) [ESP32-WROOM-32U-H4](#) [ESP32-PICO-MINI-02U-N8R2](#) [ESP32-C6-WROOM-1-N4](#) [ESP32-C6-WROOM-1U-N4](#)
[ESP32-C6-WROOM-1-N8](#) [BE200.NGWG.NV](#) [BE200.NGWG](#) [BE202.NGWG.NV](#) [BE200.NGWG.NVX](#) [AX411.NGWG.NV](#) [AX210.D2WG](#)
[AX210.NGWG.NVX](#) [AX211.NGWG](#) [EC200UEUAA-N05-TA0AA](#) [SC20ELSATEA-8GB-UGAD](#) [SG560DEUPA-U61-TA0AA](#)
[AX211.NGWG.NV](#) [ISM43340-M4G-L44-10CF-C6.2.1.11](#) [KG100SABMD](#) [BC40P](#) [S007-PIN254](#) [S007-PIN127](#) [ESP32-C3-12F](#)
[FC41DAHMD](#) [EWM-W179M201E](#) [ESP32-C6-WROOM-1U-N8](#) [ATWILC3000-MR110CA](#) [RS9113-NBZ-D5W](#) [ATWINC3400-](#)
[MR210UA122](#) [ESP32-WROOM-32](#) [AMPAK AP12356 WIFI/BT KIT](#) [AIW-154BN](#) [AIW-165BN](#) [AIW-166K1](#) [AIW-166K2](#) [AIW-166K3](#)
[AIW-166K4](#) [AIW-355 DQ-N01](#) [AIW-355 DQ-C01](#) [EWM-W159M201E](#) [EWM-W192K1](#) [EWM-W192K2](#) [W106C](#)