



4cm Black Fan

40 x 20mm, lo-noise, 12v, 3-pin, enter bearing, medium speed.

Product Code: AK-4020MS

[Where to Buy !\[\]\(17413706fd4997a1a4bdf85c6864eee1_img.jpg\)](#)

General Information

Application	PC case or heatsink fan
Dimension	40 x 40 x 20mm
Bearing	EBR Bearing
Speed	5000 RPM
Max Airflow	5.17 CFM
Max Static Pressure	2.82 mm-H ₂ O
Sound Level	25.0 dB(A)
Rated Voltage for Fan	12V DC
Rated Current for Fan	0.1 A
Fan Connector	3-Pin
Fan Life	40,000 hours
Warranty	2 years
Product Code	AK-4020MS

AKASA (@akasa_tech)



DISCOVER

About Akasa
Where to Buy
Press Room

SUPPORT



Legacy Products
Contact Us
Terms and Privacy

STAY UP TO DATE!

Subscribe now for free alerts on newly added products, exclusive deals and more.

name@example.com



 ENGLISH 

© AKASA ALL RIGHT RESERVED.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [DC Fans](#) category:

Click to view products by [Akasa](#) manufacturer:

Other Similar products are found below :

[F1238H24B-FHR](#) [F1238X24B1-FSR-TTL](#) [8312R](#) [G9225S05B2-FSR](#) [9274310103](#) [PMD1204PBB1-A \(2\).GN](#) [AUB0612L](#) [KD1204PKB3](#)
[\(2\).GN](#) [G4020H05B2-RSR-EM](#) [298DM-2LP11-000](#) [298DS-2LP11-000A](#) [AUB0912H-F00](#) [6222N](#) [USTF501005HW](#) [8412GLV](#) [8412NGL-](#)
[12](#) [4114N/12HHR-297](#) [6448-384](#) [PMD2408PMB1-A\(2\).F.GN](#) [RACK0224](#) [3258JH](#) [4114N/17-251](#) [622/2N](#) [4318/2R](#) [4412F/2D](#) [OD127AP-](#)
[28HTB](#) [424JMU](#) [EF40101BX-1000U-G99](#) [4414/2HH](#) [AQ0612MB-A70GL\(T\)#22](#) [9GA0924L4021](#) [9GA0924M4021](#) [9GA0924M4011](#)
[9GA0912M4D011](#) [9GA0912F4021](#) [9GA0912H4D011](#) [9GA0824L20021](#) [9GA0824L20011](#) [9GA0812A2002](#) [9GA0812B2D001](#)
[9GA0812L20021](#) [9WP1248M1021](#) [9GA0824L2D001](#) [9GA0912W402](#) [9GA0912M402](#) [9GA0824B2D001](#) [9GA0824A20021](#)
[9GA0912W4021](#) [9GA0924W402](#) [9GA0812L2D0011](#)