




©akasa

6cm Black Fan - Retail

60 x 25mm, lo-noise, 12v, 3-pin, sleeve bearing, medium speed.

Product Code: AK-6025MS



[Where to Buy](#) 

[OVERVIEW](#)

[SPECIFICATION](#)

[REVIEWS](#)

[SUPPORT](#)

[RELATED PRODUCTS](#)



General Information

Application	PC case or heatsink fan
Dimension	60 x 60 x 25 mm
Bearing	EBR Bearing
Speed	3000 RPM
Max Airflow	13.67 CFM
Max Static Pressure	2.57 mm-H ₂ O
Sound Level	21.79 dB(A)
Rated Voltage for Fan	12V DC
Rated Current for Fan	0.09 A
Fan Connector	3-Pin
Fan Life	30,000 hours
Product Code	AK-6025MS

AKASA (@akasa_tech)



DISCOVER

About Akasa
Where to Buy
Press Room

SUPPORT

Legacy Products
Contact Us
Terms and Privacy

STAY UP TO DATE!

Subscribe now for free alerts on newly added products, exclusive deals and more.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [DC Fans](#) category:

Click to view products by [Akasa](#) manufacturer:

Other Similar products are found below :

[F1238H24B-FHR](#) [F1238X24B1-FSR-TTL](#) [8312R](#) [G9225S05B2-FSR](#) [AUB0612L](#) [G4020H05B2-RSR-EM](#) [298DM-2LP11-000](#) [298DS-2LP11-000A](#) [AUB0912H-F00](#) [6222N](#) [USTF501005HW](#) [8412GLV](#) [8412NGL-12](#) [4114N/12HHR-297](#) [6448-384](#) [PMD2408PMB1-A\(2\).F.GN](#)
[RACK0224](#) [3258JH](#) [4114N/17-251](#) [622/2N](#) [4318/2R](#) [4412F/2D](#) [OD127AP-28HTB](#) [424JMU](#) [EF40101BX-1000U-G99](#) [4414/2HH](#)
[AQ0612MB-A70GL\(T\)#22](#) [9GA0924L4021](#) [9GA0924M4021](#) [9GA0924M4011](#) [9GA0912M4D011](#) [9GA0912F4021](#) [9GA0912H4D011](#)
[9GA0824L20021](#) [9GA0824L20011](#) [9GA0812A2002](#) [9GA0812B2D001](#) [9GA0812L20021](#) [9WP1248M1021](#) [9GA0824L2D001](#)
[9GA0912W402](#) [9GA0912M402](#) [9GA0824B2D001](#) [9GA0824A20021](#) [9GA0912W4021](#) [9GA0924W402](#) [9GA0812L2D0011](#)
[9GA0812A20021](#) [9GA0824L2001](#) [9GA0824L2002](#)