




Aluminium Socket A/370 Cooler

Cooler for Intel Socket 370 & AMD Socket A

Low noise, cost effective replacement aluminium cooler for legacy AMD Athlon XP/MP and Intel Celeron/Pentium III, two point metal mounting clip.

Product Code: AK-CC1105E01

[Where to Buy](#) 

[OVERVIEW](#)

[SPECIFICATION](#)

[REVIEWS](#)

[SUPPORT](#)

[RELATED PRODUCTS](#)



Socket Type AMD Socket A, Intel Socket 370

Cooler Dimension 56.8 x 52 x 48.7 mm

Heatsink Material Aluminium

Installation Two point clip

Weight 98g

Product Code AK-CC1105ES01

Dimensions 50 x 50 x 15 mm

Bearing EBR Bearing

Fan Speed 5300 RPM

Max Airflow 13.15 CFM

Max Air Pressure 5.02 mm-H2O

Noise Level 38.0 dB(A)

Current Rating for Fan	0.19A
Voltage Rating for Fan	DC 12V
Fan Connector	3-pin
Fan Life Expectancy	50,000 hours
Warranty	2 years

AKASA (@akasa_tech)



DISCOVER

- About Akasa
- Where to Buy
- Press Room

SUPPORT

- Legacy Products
- Contact Us
- Terms and Privacy

STAY UP TO DATE!

Subscribe now for free alerts on newly added products, exclusive deals and more.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Akasa manufacturer](#):

Other Similar products are found below :

[AK-174BK-B](#) [AK-174BKT-B](#) [AK-210-BK](#) [AK-4010MS-KT05](#) [AK-4020MS](#) [AK-5010MS](#) [AK-5010MS-KT05](#) [AK-6015MS](#) [AK-675S](#) [AK-8025HS-KT05](#) [AK-8025LS-KT05](#) [AK-8025MS-KT05](#) [AK-955A-BV2](#) [AK-CB002](#) [AK-CBFA01-30](#) [AK-CBFA06-30](#) [AK-CBFA09-50BK](#) [AK-CC1101EP02](#) [AK-CC1105ES01](#) [AK-CC1107EP01](#) [AK-CC1108HP01](#) [AK-CC6308EP01](#) [AK-CC6309EP01](#) [AK-CC6601EP01](#) [AK-CC6603EP01](#) [AK-CC6606BP01](#) [AK-CC6610EP01](#) [AK-CC6615BP01](#) [AK-CC7108EP01](#) [AK-CC7122BP01](#) [AK-CC7124EP01](#) [AK-CCE-7102EP](#) [AK-CCE-7104EP](#) [AK-CCE-7105EP](#) [AK-CCE-7106HP](#) [AK-FN062](#) [AK-FN063](#) [AK-FN065](#) [AK-FN065-BKT03](#) [AK-FN073](#) [AK-FN078-KT02](#) [AK-FN091-BL](#) [AK-FN091-GN](#) [AK-FN091-RD](#) [AK-FN091-WH](#) [AK-FN093](#) [AK-FN098](#) [AK-FN099](#) [AK-FN101](#) [AK-FN107](#)