




KS12

Low profile cooler with sickle-shape fan blades

Low profile design optimised for Mini-ITX and HTPC cases. 95mm intelligent PWM fan delivers outstanding focused airflow.

Product Code: AK-CC6308EP01

Where to Buy 

[OVERVIEW](#)

[SPECIFICATION](#)

[REVIEWS](#)

[SUPPORT](#)

[RELATED PRODUCTS](#)

Socket Type	Intel LGA1150, LGA1151, LGA1155, LGA1156, LGA1200
Suggestion TDP (W)	65
Cooler Dimension	96 x 96 x 31.8 mm
Heatsink Material	Aluminium
Installation	Screws and retention backplate
Weight	184g
Product Code	AK-CC6308EP01

Dimensions	Ø96 x 16.8 mm
Bearing	EBR Bearing
Fan Speed	800 - 2800 RPM
Max Airflow	36.28 CFM
Max Air Pressure	1.7 mm-H2O

Noise Level 15 - 37.6 dB(A)

Current Rating for Fan 0.2A

Voltage Rating for Fan DC 12V

Fan Connector 4-pin PWM

Fan Life Expectancy 40,000 hours

Warranty 2 years

AKASA (@akasa_tech)



DISCOVER

- About Akasa
- Where to Buy
- Press Room

SUPPORT

- Legacy Products
- Contact Us
- Terms and Privacy

STAY UP TO DATE!

Subscribe now for free alerts on newly added products, exclusive deals and more.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Akasa](#) manufacturer:

Other Similar products are found below :

[AK-174BK-B](#) [AK-174BKT-B](#) [AK-210-BK](#) [AK-4010MS-KT05](#) [AK-4020MS](#) [AK-5010MS](#) [AK-5010MS-KT05](#) [AK-6015MS](#) [AK-675S](#) [AK-8025HS-KT05](#) [AK-8025LS-KT05](#) [AK-8025MS-KT05](#) [AK-955A-BV2](#) [AK-CB002](#) [AK-CBFA01-30](#) [AK-CBFA06-30](#) [AK-CBFA09-50BK](#) [AK-CC1101EP02](#) [AK-CC1105ES01](#) [AK-CC1107EP01](#) [AK-CC1108HP01](#) [AK-CC6308EP01](#) [AK-CC6309EP01](#) [AK-CC6601EP01](#) [AK-CC6603EP01](#) [AK-CC6606BP01](#) [AK-CC6610EP01](#) [AK-CC6615BP01](#) [AK-CC7108EP01](#) [AK-CC7122BP01](#) [AK-CC7124EP01](#) [AK-CCE-7102EP](#) [AK-CCE-7104EP](#) [AK-CCE-7105EP](#) [AK-CCE-7106HP](#) [AK-FN062](#) [AK-FN063](#) [AK-FN065](#) [AK-FN065-BKT03](#) [AK-FN073](#) [AK-FN078-KT02](#) [AK-FN091-BL](#) [AK-FN091-GN](#) [AK-FN091-RD](#) [AK-FN091-WH](#) [AK-FN093](#) [AK-FN098](#) [AK-FN099](#) [AK-FN101](#) [AK-FN107](#)