




NEW

Copper Core Cooler for Intel® LGA1700

Copper core cooler for Intel® LGA 1700 processors using an open frame 90mm PWM twin ball bearing fan for lo-noise and reliable performance cooling. Intel® push-pins are used for easy mounting and secure retention.

Product Code: AK-CC6606BP01

Where to Buy 

[OVERVIEW](#)

[SPECIFICATION](#)

[REVIEWS](#)

[SUPPORT](#)

[RELATED PRODUCTS](#)



General Information

Socket Type	Intel LGA1700
Suggestion TDP (W)	125
Cooler Dimension	94.8 x 94.8 x 63.2 mm
Heatsink Material	Aluminium fins with copper core
Installation	Push-pins
Weight	439.1g
Product Code	AK-CC6606BP01

Fan Specification

Dimensions	Ø90 x 25 mm
Bearing	Two Ball Bearing
Fan Speed	500 - 3400 RPM
Max Airflow	40.90 CFM
Max Air Pressure	3.81 mm-H ₂ O

Noise Level 19 - 36 dB(A)

Current Rating for Fan 0.38A


Voltage Rating for Fan DC 12V

Connector 4-pin PWM

Fan Life Expectancy 80,000 hours

Warranty 2 years

AKASA (@akasa_tech)



DISCOVER

About Akasa
Where to Buy
Press Room

SUPPORT

Legacy Products
Contact Us
Terms and Privacy

STAY UP TO DATE!

Subscribe now for free alerts on newly added products, exclusive deals and more.

name@example.com



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Akasa](#) manufacturer:

Other Similar products are found below :

[AK-174BK-B](#) [AK-174BKT-B](#) [AK-210-BK](#) [AK-4010MS-KT05](#) [AK-4020MS](#) [AK-5010MS](#) [AK-5010MS-KT05](#) [AK-6015MS](#) [AK-675S](#) [AK-8025HS-KT05](#) [AK-8025LS-KT05](#) [AK-8025MS-KT05](#) [AK-955A-BV2](#) [AK-CB002](#) [AK-CBFA01-30](#) [AK-CBFA06-30](#) [AK-CBFA09-50BK](#) [AK-CC1101EP02](#) [AK-CC1105ES01](#) [AK-CC1107EP01](#) [AK-CC1108HP01](#) [AK-CC6308EP01](#) [AK-CC6309EP01](#) [AK-CC6601EP01](#) [AK-CC6603EP01](#) [AK-CC6606BP01](#) [AK-CC6610EP01](#) [AK-CC6615BP01](#) [AK-CC7108EP01](#) [AK-CC7122BP01](#) [AK-CC7124EP01](#) [AK-CCE-7102EP](#) [AK-CCE-7104EP](#) [AK-CCE-7105EP](#) [AK-CCE-7106HP](#) [AK-FN062](#) [AK-FN063](#) [AK-FN065](#) [AK-FN065-BKT03](#) [AK-FN073](#) [AK-FN078-KT02](#) [AK-FN091-BL](#) [AK-FN091-GN](#) [AK-FN091-RD](#) [AK-FN091-WH](#) [AK-FN093](#) [AK-FN098](#) [AK-FN099](#) [AK-FN101](#) [AK-FN107](#)