



### EL2809-0015 | 16-Channel Digital Output Terminal, 24 V<sub>DC</sub>, 0.35 A

The EL2809-0015 digital output terminal connects the binary control signals from the automation device on to the actuators at the process level with electrical isolation. The EL2809-0015 has sixteen channels that indicates its signal state via light emitting diodes.

If the terminal is used as a replacement for an EL2809, a change of the TwinCAT configuration is not necessary (default settings).

Technical data	EL2809-0015
Digital outputs	16
Connection technology	1-wire
Nominal output voltage	24 V <sub>DC</sub> (-15% / +20%)
Load type	ohmic, inductive
Output current per channel	maximum 0.35 A per channel (not short-circuit proof), $\Sigma$ 4,5 A
Switching times	T <sub>ON</sub> : 10 µs typ.; T <sub>OFF</sub> : 25 µs typ.
Current consumption from the E-bus	typ. 140 mA
Current consumption power contacts	typ. 35 mA + load
Electrical isolation	500 V (E-bus / field voltage)
Bit width in the process image	16 output bits
Distributed clocks	-
Configuration	no address or configuration setting
Permissible ambient temperature range during operation	0°C ... +55°C
Permissible ambient temperature range during storage	-25°C ... +85°C
Permissible relative humidity	95%, no condensation
Weight	approx. 70 g
Dimensions (W x H x D)	approx. 15 mm x 100 mm x 70 mm (width aligned: 12 mm)
Mounting	on 35 mm mounting rail conforms to EN 60715
Vibration / shock resistance	conforms to EN 60068-2-6 / EN 60068-2-27
EMC resistance burst / ESD	conforms to EN 61000-6-2 / EN 61000-6-4
Protection class / installation position	IP20 / variable
Markings / approvals*	CE, UKCA, cULus, EAC

\*) Real applicable approvals/markings see type plate on the side (product marking).

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Ethernet Modules](#) category:*

*Click to view products by [Beckhoff](#) manufacturer:*

Other Similar products are found below :

[I350T4V2](#) [GX-OD1612](#) [TDKEZW3](#) [I350T2V2](#) [V23993-USB1029A](#) [I350T4V2BLK](#) [I350T2V2BLK](#) [FC6A-PH1](#) [GX-ID1611](#)  
[BCM84794A1KFSBG](#) [X710T2L](#) [X710T4LBLK](#) [BOXER-6614-A1M-1110](#) [ED-593](#) [EL2809-0015](#) [RSB20-0800T1T1SAAB](#) [1005957](#)  
[1005TX](#) [1006191](#) [104TX](#) [105TX](#) [108TX](#) [MESP211T](#) [WIZ107SR\\_TTL](#) [SFP-100FX-M-2KM-T](#) [ES-320](#) [851-10912](#) [MOD-54417-100IR](#)  
[TDKEZW5](#) [855-10619](#) [2003025](#) [2003037](#) [2013040](#) [2013050](#) [2014120](#) [2014126](#) [2014130](#) [2014134](#) [2014140](#) [2014150](#) [2017008](#) [2018108](#)  
[2032008](#) [2036040](#) [2036050](#) [750-1405](#) [EKI-5626C-AE](#) [24030060000](#) [24030082110](#) [70002039](#)