



Top view

## BK1250 | “Compact” coupler between E-bus and K-bus Terminals



The BK1250 is a “Bus Coupler in terminal housing” for mixed application of EtherCAT Terminals (ELxxxx) and standard Bus Terminals (KLxxxx) in a bus station. It enables implementation of compact and cost-effective control solutions. The wide range of Bus Terminals can thus be optimally combined with the communication speed and large bandwidth of EtherCAT Terminals. Up to 64 Bus Terminals (with K-bus extension up to 255) can be connected to a BK1250. The Bus Coupler recognises the connected Bus Terminals and automatically allocates them into the EtherCAT process image.

Technical data	BK1250
Number of Bus Terminals	64 (255 with K-bus extension)
Max. number of bytes fieldbus	1024 byte input and 1024 byte output
Digital peripheral signals	8,192 inputs/outputs
Analog peripheral signals	256 inputs/outputs
Protocol	EtherCAT
Configuration possibility	via KS2000 or EtherCAT (ADS)
Data transfer rates	100 Mbaud
Bus interface	via E-bus contacts
Power supply	24 V DC (-15 %/+20 %)
Input current	70 mA + (total K-bus current)/4, 200 mA max.
Starting current	approx. 2.5 x continuous current
Recommended fuse	≤ 10 A
Current supply K-bus	500 mA
Power contacts	24 V DC max./10 A max.
Electrical isolation	500 V (power contact/supply voltage/Ethernet)
Weight	approx. 55 g
Operating/storage temperature	-25...+60 °C/-40...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Approvals	CE, UL, Ex

Accessories	
KS2000	configuration software for extended parameterisation
Cordsets	cordsets and connectors
FC9001-0010   FC9011	Ethernet PCI fieldbus cards

Related products	
<b>BK1120</b>	EtherCAT "Economy plus" Bus Coupler for up to 64 Bus Terminals (255 with K-bus extension)
<b>BK1150</b>	EtherCAT "Compact" Bus Coupler for up to 64 Bus Terminals (255 with K-bus extension)

System	
<b>EtherCAT</b>	For further EtherCAT products please see the <a href="#">system overview</a> .

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Controllers](#) category:*

*Click to view products by [Beckhoff](#) manufacturer:*

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)  
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)  
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)  
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)  
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)  
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)