



Top view

EL6751 | CANopen master/slave terminal



The Terminal enables within an EtherCAT Terminal network the integration of any CANopen devices and can either be master (EL6751) or slave (EL6751-0010). In addition, general CAN messages can be sent or received – without having to bother with CAN frames in the applications program. The terminal has a powerful protocol implementation with many features:

- All CANopen PDO communication types are supported: event driven, time driven (using an event timer), synchronous, polling.
- synchronisation with the PC controller's task cycle
- SYNC cycle with quartz precision for drive synchronisation, zero cumulative jitter
- parameter communication (SDO) at start-up and when running
- emergency message handling, guarding and heartbeat
- powerful parameter and diagnostics interfaces
- online bus load display

Like the FC5101 CANopen PCI card, the EL6751 can be used for connection to CANopen networks. The terminal, however, enables a more space-saving implementation since no PCI slots are required in the Industrial PC.

Technical data	EL6751	EL6751-0010
Technology	CANopen master terminal	CANopen slave terminal
Fieldbus	CANopen	
Number of fieldbus channels	1	
Data transfer rates	10, 20, 50, 100, 125, 250, 500, 800, 1000 kbaud	
Interfaces	D-sub connector, 9-pin according to CANopen specification, galvanically decoupled	
Communication	CANopen network master and CANopen manager, optionally CANopen slave	
Hardware diagnosis	status LEDs	
Distributed clocks	–	
Current consumption power contacts	–	
Current consumption E-bus	typ. 230 m A	
Special features	status LEDs, CANopen network master, CANopen Manager, supports RAW-CAN	status LEDs, CANopen slave
Weight	approx. 70 g	
Operating/storage temperature	-25...+60 °C/-40...+85 °C	
Relative humidity	95 %, no condensation	
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27	
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4	
Protect. class/installation pos.	IP 20/variable	
Approvals	CE, UL, Ex	

System	
CANopen	For further CANopen products please see the system overview .

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)