



KL3204 | 4-channel input terminal PT100 (RTD)

The KL3204 analog input terminal allows resistance sensors to be connected directly. The Bus Terminal's circuitry can operate the sensors using 2-wire connection techniques. Linearisation over the full temperature range is realised with the aid of a microprocessor. The temperature range can be selected freely. The Bus Terminals standard settings are: resolution 0.1 °C in the temperature range of PT100 sensors. The error LEDs indicate sensor faults (e.g. a broken wire). The KL3204 version combines four channels in one housing.

Technical data	KL3204 KS3204
Number of inputs	4
Power supply	via the K-bus
Technology	2-wire
Sensor types	PT100, PT200, PT500, PT1000, Ni100, Ni120, Ni1000 resistance measurement (e.g. potentiometer, 10 Ω...1.2/5 kΩ)
Connection method	2-wire
Measuring range	-200...+850 °C (PT sensors); -60...+250 °C (Ni sensors)
Resolution	0.1 °C per digit
Conversion time	~ 250 ms
Measuring current	typ. 0.5 mA
Measuring error	< ±1 °C
Electrical isolation	500 V (K-bus/signal voltage)
Current consumption power contacts	– (no power contacts)
Current consumpt. K-bus	typ. 60 mA
Bit width in the process image	input: 4 x 16 bit data (4 x 8 bit control/status optional)
Configuration	no address setting, configuration via Bus Coupler or controller
Special features	open-circuit recognition
Weight	approx. 70 g
Operating/storage temperature	-25...+60 °C/-40...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Pluggable wiring	for all KSxxxx Bus Terminals
Approvals	CE, UL, Ex, GL

Special terminals	
KL3204-0014	PT1000
KL3204-0021	PT100 in Siemens S5 format
KL3204-0025	Ni1000, 4-channel
KL3204-0029	Ni1000 per Landis&Staeft characteristic curve (Siemens, 100° corresponds to 1,500 Ω)
KL3204-0030	4-channel input terminal NTC (10 kΩ) for resistance sensors, 16 bit, 2-wire system

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)