



KL6401 | LON Bus Terminal

The KL6401 LON Bus Terminal enables direct connection of LON devices. The network variables of the connected devices are available for the Bus Coupler or the higher-level bus system. This simplifies the data exchange between a variety of systems and a LON network. Status LEDs directly indicate the bus status. The LON terminal operates independent of the bus system used. Several KL6401 can be used with a single Bus Coupler or a Bus Terminal Controller. The KL6401 supports 62 SNVTs. All SNVT types can be configured as input or output variable via the KS2000 software. The KS2000 software generates an XIF file that is integrated in an LON tool.

Technical data	KL6401
Technology	LON
Number of channels	1
Data transfer standard	FTT-10, LPT
Data transfer channels	1
Network variables	62 (standard network variables SNVTs), max. 15 LON devices
Data transfer rates	78 kbit/s
Bus segment length	500 m
Bus access	CSMA
Current consumpt. K-bus	typ. 55 mA
Current consumption power contacts	only load
Electrical isolation	500 V (K-bus/LON-bus)
Bit width in the process image	input/output: 36 bytes
Configuration	KS2000, LonMaker or another LON Tool, TwinCAT (function blocks)
Nominal voltage	24 V DC (-15 %/+20 %)
Special features	15 devices; TwinCAT library: TwinCAT PLC LON
Weight	approx. 85 g
Operating/storage temperature	0...+55 °C/-25...+85 °C
Relative humidity	95 %, no condensation
Vibration/shock resistance	conforms to EN 60068-2-6/EN 60068-2-27
EMC immunity/emission	conforms to EN 61000-6-2/EN 61000-6-4
Protect. class/installation pos.	IP 20/variable
Approvals	CE, UL, Ex

Accessories	
TwinCAT PLC LON	The library is installed free of charge together with TwinCAT from V2.11 Build 2229 (R3 and x64 engineering).

System	
subsystem	For further subsystem products please see the system overview .

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Controllers](#) category:

Click to view products by [Beckhoff](#) manufacturer:

Other Similar products are found below :

[CS1WCN223](#) [CS1WCN713](#) [CS1WKS001E](#) [61F-11NH](#) [61FGPN8DAC120](#) [61F-GP-NT AC110](#) [61F-GPN-V50-AC110](#) [70177-1011](#) [F03-03](#)
[HAS B](#) [F03-03 HAS C](#) [F03-31](#) [81513201](#) [81513535](#) [81550401](#) [FT1A-C12RA-W](#) [88981106](#) [H2CAC24A](#) [R88A-CAGA005S](#) [R88A-](#)
[CRGB003CR-E](#) [R88ARR080100S](#) [R88A-TK01K](#) [DCN1-1](#) [DTB4896VRE](#) [DTB9696CVE](#) [DTB9696LVE](#) [MR-50LF+](#) [E53-AZ01](#) [E53E8C](#)
[E5CWLQ1TCAC100240](#) [B300LKL21](#) [NE1ASCPU02EIPVER11](#) [NE1SCPU01](#) [NE1SDRM21U](#) [NSCXDC1V3](#) [NSH5-232CW-3M](#)
[NT20SST122BV1](#) [NV3Q-SW41](#) [NV4W-ATT01](#) [NV-CN001](#) [OAS-160-N](#) [K31S6](#) [K33-L1B](#) [K3TX-AD31A](#) [L595020](#) [SRS2-1](#) [G32X-V2K](#)
[26546803](#) [26546805](#) [26546831](#) [CJ1W-OD204](#)