

1300 Series MMCX

50 Ohm Cable and PCB Connectors



Bomar products, like the 1300 Series MMCX 50 Ohm Cable and PCB Connectors, are now sold under the Win™ brand from Winchester Interconnect™.

Product Description

Winchester Interconnect's 1300 Series 50 Ohm MMCX Connectors are 30% smaller than MCX Connectors.

Due to their small size, MMCX Connectors can be used in a wide range of applications including Test and Measurement, Mil-Aero, Satellite Communication, Wireless Communication, and Medical Equipment.

Our 1300 Series 50 Ohm MMCX Connectors are designed in accordance with European Specification CECC 22000 and feature a "Snap-On" interface designed for a frequency range of DC to 6 GHz.

Male cable plug connectors are available in straight and right-angle designs for popular flexible and semi-rigid cables.

Printed circuit board (PCB) connectors are available in straight and right-angle through-hole solder and also in our unique E-Snap® Edge-Mount design.



- Quick connect disconnect snap-on mating reduces installation time.
- Due to their miniature size, MMCX Connectors are ideal for high density applications requiring a very small RF interconnect.

 **Winchester**
Interconnect.

We Energize Innovation.

Specifications

Electrical Impedance 50 Ohms	Contact Resistance Center ≤ 10 Megohms Outer ≤ 5 Megohms	Engagement Force ≤ 3.4 lbs. (15N)	Contact Finish Gold	Moisture Resistance MIL-STS-202, Method 105
Frequency DC to 6 GHz	Insulation Resistance 1000 Megohms Min	Disengagement Force ≥ 1.4 lbs. (6N)	Insulator PTFE	Corrosion MIL-STD-202, Method 101
RF-Leakage 60 dB Min at 1 GHz	Mechanical Mating Snap-On Coupling	Durability 500 Cycles Min	Crimp Ferrule Copper or Brass Nickel Plated	Mechanical Shock MIL-STD-202, Method 101
Dielectric Withstanding Voltage 500 VRMS at sea level	Contact Captivation 2.3 lbs.	Material Body Brass	Environmental Temperature Range -55°C to +155°C	Humidity MIL-STD-202, Method 101
VSWR <i>Straight</i> 1.15 Max DC - 4 GHz <i>Right-Angle</i> 1.4 Max 4 - 6 GHz		Body Finish Nickel	Thermal Shock MIL-STD-202, Method 107	

Part Numbers

Part Number	Straight and Right-Angle Cable Plugs	Crimp Tool	Hex Size
1310A204F	Straight Cable Plug for RG178, RG196	BDHD200	Solder / 0.128
1310A204M	Straight Cable Plug for RG174, RG316, LMR100	BDHD200	Solder / 0.128
1310A204S	Straight Cable Plug for RD316	BDHD200	Solder / 0.151
1320A204-405	Straight Cable Plug for RG405 Semi-Rigid	Solder	Solder
1320A204-047	Right-Angle Cable Plug for 0.047 Semi-Rigid	Solder	Solder
1313A204F	Right-Angle Cable Plug for RG178, RG196	BDHD200	Solder / 0.128
1313A204M	Right-Angle Cable Plug for RG174, RG316, LMR100	BDHD200	Solder / 0.128
1313A20MS	Right-Angle Cable Plug for RD316	BDHD200	Solder / 0.151
1313A204-405	Right-Angle Cable Plug for RG405	Solder	Solder
1313A204-047	Right-Angle Cable Plug for 0.047 Semi-Rigid	Solder	Solder

Part Number	Printed Circuit Board Connectors	PCB Thickness	Packaging
1362A514	Vertical, MMCX, Plug, 0.155" Solder Tail	0.062"	Single
1361A514	Vertical, MMCX, Jack, 0.155" Solder Tail	0.062"	Single
1361E514	Edge-Mount, MMCX, Jack	0.062"	Single
1364A514	Right-Angle, MMCX, Jack, 0.155" Solder Tail	0.062"	Single
1361E504	E-Snap® Edge-Mount, MMCX, Jack	0.062"	Single

Win  Bomar products are now under the Win™ brand from Winchester Interconnect.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [RF Connectors / Coaxial Connectors](#) category:

Click to view products by [Bomar Interconnect](#) manufacturer:

Other Similar products are found below :

[8915-1511-000](#) [89674-0827](#) [6001-7071-019](#) [6002-7051-003](#) [6002-7551-202](#) [6059674-1](#) [619550-1](#) [630059-000](#) [M39030/3-01N](#) [6500-7071-046](#) [6769](#) [CX050L2AQ](#) [7002-1541-010](#) [7002-1542-011](#) [7004-1512-000](#) [7009-1511-004](#) [7010-1511-000](#) [7029-1511-060](#) [7101-1541-010](#) [7101-1571-002](#) [7145-1521-002](#) [7203-1571-003](#) [7209-1511-011](#) [7210-1511-015](#) [7210-1511-019](#) [73137-5015](#) [73216-2241](#) [73404-2300](#) [7405-1521-005](#) [7405-1521-802](#) [8527](#) [8547](#) [FS11V](#) [877931](#) [8808-1511-001](#) [9049-9513-000](#) [9074-9513-000](#) [9101-9573-002](#) [910A205F](#) [9130-9573-002](#) [PL11SC-026](#) [PL375-33](#) [PL40-5](#) [PL74C-221](#) [PL75MC-217](#) [PL803-7](#) [980-8666-005](#) [1200690078](#) [1-201144-1](#) [R107003010W](#)