

1250 Rocker Switches 10A 250Vac



10(6)A 250Vac T100
6A 400Vac T100
1A 30Vdc



UL CSA 10A 250Vac
UL CSA 16A 250Vac Resistive
UL CSA 125Vac 1/2hp
UL CSA 1A 30Vdc
UL 100°C, file E45221, CSA file LR10990

In house test

Inrush 75A to EN61058-1



RoHS compliant

3mm contact gap
 Technical data on pages 4 & 5

- ▶ Standard rocker switch
- ▶ Double pole in single pole body
- ▶ Snap in or sub panel mount
- ▶ Integral terminal barrier
- ▶ Push on or PCB terminals
- ▶ High inrush tolerance
- ▶ Panel cut out:
 27.2 x 12.4 (snap in)
 26.3 x 12.4 (sub panel mount)



C1250AP ---



C1250AN ---











rocker switches

B BLACK
W WHITE
B BLACK
W WHITE
G GREY

C 1250 A P B B 085W

ORDER FORMAT


TERMINAL CODE FUNCTION CODE ROCKER CODE BODY CODE BODY COLOR ROCKER COLOR LEGEND & OPTIONS

TERMINAL	FUNCTION	ROCKER	BODY	OPTIONS						
<p>C</p>  <p>6.3 x 0.8</p>	 <p>On when pressed over terminal 1</p> <p>1250</p>  <p>ON - OFF Double pole</p> <p>Poles are 9.0mm between centres.</p>	<p>A Curved</p>  <p>Shown in N body</p>	<p>N</p> <p>Panel cut-out Bezel</p>  <p>Sub-panel Facia</p> <p>Panel thickness Dim X</p> <table border="0"> <tr> <td>0.75-1.24</td> <td>26.1/26.2</td> </tr> <tr> <td>1.25-1.99</td> <td>26.3/26.4</td> </tr> <tr> <td>2.00-3.00</td> <td>26.7/26.8</td> </tr> </table>	0.75-1.24	26.1/26.2	1.25-1.99	26.3/26.4	2.00-3.00	26.7/26.8	<p>Finish Matt finish only.</p> <p>Color Call factory for custom colors. A full range is available for large orders.</p> <p>Legend printing Select from the examples or call factory for custom legends.</p> <p>Contact factory for suggested terminals.</p>
0.75-1.24	26.1/26.2									
1.25-1.99	26.3/26.4									
2.00-3.00	26.7/26.8									
<p>X</p>  <p>PCB 0.8sq (N body only)</p>	 <p>On when pressed over terminal 1</p> <p>1250SP</p>  <p>ON - OFF Single pole</p>	<p>P</p>  <p>Shown in P body</p>	<p>P</p> <p>Panel cut-out Bezel</p>  <p>Panel thickness</p> <p>0.75-3.00</p>							


Cut-outs must be punched in the direction of insertion

Dimensions (mm)


1250AN (C terminals shown)




1250AN (X terminals shown)



1250AP (C terminals shown)



Connector Housing F1344



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Rocker Switches](#) category:

Click to view products by [Bulgin](#) manufacturer:

Other Similar products are found below :

[LTI LA6E-1S-WH-RC-FN12VXCR1](#) [6-1571986-9](#) [8007K26N324V52](#) [8055K32Z7V](#) [8055K52Z7V](#) [8138K20E6M50](#) [84206L](#) [84312LX](#)
[PREDD5-07F-BB0GW](#) [999-16716-002](#) [999-16716-003](#) [999-16716-004](#) [A101J1V3Q004](#) [A101J2ZQ004](#) [A101J4ZQ004](#) [A101J51CB0004](#)
[A103J1ZQ004](#) [A201J1AQ004](#) [A201J3ZB004](#) [A201J50ZQ004](#) [A203J51ZQ0004](#) [A435S1YZQ](#) [H8500XBBBBL-A](#) [H8653VBBG2577W](#)
[HB130CHNWWNAAC](#) [R13112ABB-602W](#) [1251.0303](#) [AE205J60V3B004](#) [1352.0107](#) [1571099-3](#) [1571987-4](#) [1571987-5](#) [1571989-7](#)
[1571988-5](#) [B123J77V7B2](#) [B226J50W4Q22P](#) [B433J37ZQ22M](#) [160212E](#) [1634200-7](#) [1801.1164](#) [1839.1502](#) [PANEL-PLUG-VHP-BLACK](#)
[PANEL-PLUG-VHP-WT](#) [K1ABBSCADN](#) [KG312A2DXD246X](#) [250011E714](#) [2600HM11E](#) [2600R21E](#) [2637LH/2A7/122048L0](#)
[2639LH/2A7/127000L0](#)