

# CT2765

## Coaxial Adapter In-Series

BNC, female to female, General Purpose

### Description

General Purpose BNC barrel, female to female, 50 in-series coaxial adapter.

- General Purpose
- Body: Brass, Nickel Plt.
- Contact: Brass, Gold Plt.



*Technical data subject to change.*

© Cal Test Electronics 2018.

[caltestelectronics.com](http://caltestelectronics.com)

# Datasheet

**Cal Test**  
ELECTRONICS 

All specifications apply to the unit after a temperature stabilization time of 20 minutes over an ambient temperature range of 25°C ± 5°C.

### Specifications

<b>Connector Grade</b>	General Purpose
<b>Impedance</b>	50
<b>Frequency Range</b>	DC to 4 GHz
<b>VSWR Max</b>	1.30:1 - DC to 4 GHz
<b>Insertion Loss Max</b>	0.2 dB
<b>Temperature (degrees)</b>	-20 to +80C
<b>RoHS (2011/65/EU)</b>	Compliant

Specifications are subject to change without notice. To ensure the most current version of this manual, please download the current version from our website: [caltestelectronics.com](http://caltestelectronics.com)

*Technical data subject to change.*

© Cal Test Electronics 2018.

[caltestelectronics.com](http://caltestelectronics.com)



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [RF Adapters - In Series](#) category:*

*Click to view products by [Cal Test](#) manufacturer:*

Other Similar products are found below :

[5918-1103-000](#) [651A505](#) [R114703000W](#) [R127871001](#) [R143730700](#) [R222M40050](#) [R223703180](#) [HRM-513S](#) [KC-79-179](#) [KN-99-14](#) [252169-75](#) [252186](#) [R127703001](#) [R127.870.001](#) [R142723000](#) [R161703000](#) [R161715000W](#) [R405005000](#) [BJ38](#) [KA-99-56](#) [KC-59-270](#) [KC-59-284](#) [KC-79-131](#) [KC-99-35](#) [KC-99-40](#) [5919-9503-003](#) [73415-4212](#) [756-18-9](#) [R143.183.000](#) [R164705000](#) [R124720003W](#) [R142723000W](#) [R222M40060](#) [4-1532004-7](#) [755-93-7](#) [033-0219-0001](#) [3094317](#) [5917-9103-000](#) [920-56](#) [R222705239](#) [R143753000W](#) [R143720000](#) [R223703080W](#) [9176-9113-000](#) [R222M40107](#) [R114009000](#) [R124720003](#) [AD48](#) [ADP-NF-NF](#) [R142562290](#)