

CT4076-NA

High Voltage Differential Probe 35 MHz / ± 7.5 kV

Datasheet

Overview:

Use the CT4076-NA 35-MHz differential probe to make safe and accurate floating measurements with an oscilloscope. The CT4076-NA differential probe allows conventional earth-grounded oscilloscopes to be used for floating signal measurements of up to ± 7.5 kV for both differential and common mode voltage.



Features:

- 35 MHz bandwidth
- Selectable attenuation settings of 100x or 1000x
- Up to ± 7.5 kV differential and common mode voltage
- Compatible with most oscilloscopes
- Powered by included 9 VDC mains adapter

Specifications

Operating Parameters	
Bandwidth	35 MHz
Rise Time	10 ns
Attenuation	100x / 1000x
Accuracy	±2%
AC CMRR	-80 dB @ 60 Hz -60 dB @ 100 Hz -50 dB @ 1 MHz
Input Impedance	Between inputs: 50 MΩ // 1.3 pF Each input to ground: 25 MΩ // 2.6 pF
Input Voltage	
Differential Voltage (DC+ACpk)	±750 V / ±7.5 kV
Common-Mode Voltage (DC+ACpk)	±7.5 kV or 5.5 kVrms
Absolute Max Voltage (DC+ACpk)	±7.5 kV or 5.5 kVrms
Output Voltage	
Swing	±8 V (±4 V into 50 Ω load)
Source Impedance	50 Ω
General	
Power Supply	External 9 VDC power supply
Power Consumption	200 mA about (9 VDC)
Operating Temperature/ Humidity	0°C to 50°C / 10% to 85% RH
Storage Temperature/Hu- midity	-30°C to 70°C / 10% to 90% RH
Cable Length	100 cm
Input Leads Length	60 cm each
Weight	350 g
Dimensions	220 x 85 x 30 mm

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Test Probes](#) category:

Click to view products by [Cal Test](#) manufacturer:

Other Similar products are found below :

[6214](#) [6474](#) [815003](#) [923832-BK-B](#) [P-KIT-1](#) [KT-MS001](#) [925250-R](#) [973368101](#) [972318101](#) [972318100](#) [MXHQ87WJ3000](#) [PK106-3](#) [PK2-5MM-102](#) [TAS90](#) [VL1735/45](#) [973368100](#) [972327100](#) [972327101](#) [973995100](#) [973995101](#) [CT3982B-120](#) [MO50-PINS](#) [CT4386](#) [PP023-1](#) [PK1-5MM-127](#) [PP026-1](#) [PK103](#) [PK-ZS-013](#) [P6139B-PK10](#) [PQ215](#) [PQ218](#) [RT-ZI10C](#) [TT-SI 8071](#) [TT-SI 8050](#) [TT-SI 8010A](#) [TT-SI 7005](#) [GE.3421](#) [GE.2521](#) [GE.3121](#) [GE.1511](#) [GE.1521](#) [GE.2511](#) [GE.4511](#) [HVP15B](#) [TT-SI7002](#) [4005](#) [4011](#) [4012](#) [4013](#) [4014](#)