



# CQB150-300S SERIES

## 150 WATT 2:1 INPUT

### DC-DC CONVERTERS

### SINGLE OUTPUT



## FEATURES

- \* 150W Isolated Output
- \* Efficiency to 89%
- \* Fixed Switching Frequency
- \* Regulated Outputs
- \* Remote On/Off
- \* Low No Load Power Consumption
- \* Over Temperature Protection
- \* Over Voltage/Current Protection
- \* Continuous Short Circuit Protection
- \* Quarter Brick Size meet industrial standard
- \* CE Mark Meets 2014/30/EU
- \* UL60950-1 2<sup>nd</sup> (Reinforced Insulation) Approval



MODEL NUMBER	INPUT VOLTAGE	OUTPUT VOLTAGE	OUTPUT CURRENT		INPUT CURRENT		% EFF.	CAPACITOR LOAD MAX.
			MIN.	MAX.	NO LOAD	FULL LOAD		
CQB150-300S05	180-425 VDC	5 VDC	0 mA	30 A	10 mA	580 mA	86	10000 $\mu$ F
CQB150-300S12	180-425 VDC	12 VDC	0 mA	12.5 A	10 mA	560 mA	89	8800 $\mu$ F
CQB150-300S15	180-425 VDC	15 VDC	0 mA	10 A	10 mA	560 mA	89	8800 $\mu$ F
CQB150-300S24	180-425 VDC	24 VDC	0 mA	6.3 A	10 mA	570 mA	88.5	3300 $\mu$ F
CQB150-300S28	180-425 VDC	28 VDC	0 mA	5.4 A	10 mA	570 mA	88.5	3300 $\mu$ F
CQB150-300S48	180-425 VDC	48 VDC	0 mA	3.2 A	10 mA	570 mA	89	1000 $\mu$ F

### NOTE:

1. Nominal Input Voltage 300 VDC.
2. Require a Ceramic Capacitor 2200pF Connected Between -Vin to Case for All Models.
3. An External Input Capacitor 180uF for All Models are Recommended to Reduce Input Ripple Voltage.
4. Measure at Nominal Input Voltage.



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Isolated DC/DC Converters](#) category:*

*Click to view products by [Cincon](#) manufacturer:*

Other Similar products are found below :

[ESM6D044440C05AAQ](#) [FMD15.24G](#) [PSL486-7LR](#) [Q48T30020-NBB0](#) [JAHW100Y1](#) [SPB05C-12](#) [SQ24S15033-PS0S](#) [18952](#) [19-130041](#)  
[CE-1003](#) [CE-1004](#) [GQ2541-7R](#) [RDS180245](#) [MAU228](#) [J80-0041NL](#) [DFC15U48D15](#) [XGS-0512](#) [XGS-1205](#) [XGS-1212](#) [XGS-2412](#) [XGS-](#)  
[2415](#) [XKS-1215](#) [06322](#) [NCT1000N040R050B](#) [SPB05B-15](#) [SPB05C-15](#) [L-DA20](#) [DCG40-5G](#) [QME48T40033-PGB0](#) [XKS-2415](#) [XKS-2412](#)  
[XKS-1212](#) [XKS-1205](#) [XKS-0515](#) [XKS-0505](#) [XGS-2405](#) [XGS-1215](#) [XGS-0515](#) [PS9Z-6RM4](#) [73-551-5038I](#) [AK1601-9RT](#) [VI-N61-CM](#) [VI-](#)  
[R5022-EXWW](#) [PSC128-7iR](#) [RPS8-350ATX-XE](#) [DAS1004812](#) [PQA30-D24-S24-DH](#) [VI-M5F-CQ](#) [VI-LN2-EW](#) [VI-PJW01-CZY](#)