Product Specification PDF



Date	Correct as of 23rd Feb 2021
Brand	C.K
Product	T4360
Description	Damaged Nut/Bolt Rescue Set of 10 Metric
Barcode	5013969246650
Commodity code	8204110000
Country of origin	TW



Features & Benefits

~Patented extractor inserts for Ring Spanners & Sockets ~Adapters for fixings sized 8,9,10,11,12,13,14,15,16 and 17mm ~Securely grips all round and works on fasteners with up to 85% damaged or worn corners ~Works on a range of fasteners eg. 6 point, 12 point, Hex and Spline ~Adapts just two socket/ring spanner sizes to fit 10 different fasteners (sizes 8-17mm) ~8-12mm Inserts suit 14mm wrench / 12-17mm Inserts suit 19mm wrench ~Unique Flange design to prevent fall through

Warranty

C.K products are guaranteed for 1year against imperfect materials or workmanship. Damage caused through normal wear and tear or resulting from inappropriate use, is not covered

Product Weights and Measures					
	Product only	Product & primary packaging	Secondary packaging	Transit packaging	
Item Quantity	1	1	20	40	
Width mm	70	150	180	340	
Depth mm	30	30	560	370	
Height mm	150	150	260	370	
Weight	138	194	4080	8.8	
Packaging Information	Card use	Box	Box	Case	
	Card gms	12	200	600	
	Plastic use	-	0	-	
	Plastic gms	44	0	0	
	Metal use	-	0	-	
	Metal gms	-	0	0	
	Timber use	-	0	-	
	Timber gms	-	0	0	

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Spanners category:

Click to view products by CK Tools manufacturer:

Other Similar products are found below:

74005 74008 1406504-3 1406504-4 1406504-5 1406504-7 1725859-2 9965 999-16625-001 G70515-18 1055265-1 1055267-1 1-1406504-0 1055787-1 DCH.91.251.PA TG70-18 TG70 G62748-11 DPH.99.005.2K DCP.91.045.TN 1055512-1 1055276-1 R282303020 TA-0456 DCA.91.149.0TN TA-0436 TA-0398 TOL-222901 74_Z-0-0-193 294GB-5069-17-N 74_Z-0-0-2 523200-4 294GB-5070-25-A 74_Z-0-0-79 294GB-5070-17-A 74_Z-0-0-321 TOL-171801 PR23350 1490262-2 9968 AC24VS 80117 DCN.91.149.0TK BT-A-6010CAGE R282340000 BT-BS-609WT BT-A-6000B R282303000 BT-BS-610R BT-BS-610RT