



Directive 2002/95/EC  
"RoHS"  
Compliant

No. of pos.	A ±0.2	B ±0.1	C ±0.2	D ±0.1	E	Part-NO.
10	32.00	27.94	17.82	4x2.54=10.16	50.00	141A10379X
14	37.08	33.02	22.90	6x2.54=15.24	55.00	141A10389X
16	39.62	35.56	25.44	7x2.54=17.78	57.60	141A10399X
20	44.70	40.64	30.52	9x2.54=22.86	62.50	141A10409X
26	52.32	48.26	38.14	12x2.54=30.48	70.10	141A10419X
34	62.48	58.42	48.30	16x2.54=40.64	80.30	141A10429X
40	70.10	66.04	55.92	19x2.54=48.26	87.90	141A10439X
50	82.80	78.74	68.62	24x2.54=60.96	100.70	141A10449X
60	95.50	91.44	81.32	29x2.54=73.66	113.40	141A10459X
64	100.58	96.52	86.40	31x2.54=78.74	118.52	141A12339X

**NOTES:**

- INSULATORS: PBT GV, V0 UL 94, GREY
- CONTACTS: PHOSPHOR BRONCE
- OPERATING TEMPERATURE RANGE: -40°C TO +105°C
- CURRENT CARRYING CAPACITY: 1A
- TEST VOLTAGE: 1000 Veff.
- CONNECTOR IS PART MARKED: PART-NO. CONEC ABC

APPROVAL # FREIGABE # DEBLOCAGE # AUTORIZACION # APPROVAL

CUSTOMER APPROVAL DATE:

NAME: TITLE:

COMPANY NAME:

APPROVAL # FREIGABE # DEBLOCAGE # AUTORIZACION # APPROVAL

THIS DRAWING MAY NOT BE COPIED OR REPRODUCED IN ANY WAY, AND MAY NOT BE PASSED ON TO A THIRD PARTY, WITHOUT WRITTEN PERMISSION. OWNERSHIP AND COPYRIGHT OF CONEC GmbH DO NOT ALTER CAD DRAWING BY HAND

2 x b	Ä 3115	24.09.2008	lehmen
a	Origin		
rev.	description	date	name

tolerance		scale: 2:1
		material: SEE NOTES
2002	date	name
drawn	24.07.	Parei
appd.	24.07.	E. Mickenbecker
norm	DIN 41651	
d-old		
title:		dwg no: AutoCAD 2000 DIN-A
HEADER		3
10-64pos. STRAIGHT SOLDER PINS with long latch		sh: 1/1
part no: SEE TABLE		



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Headers & Wire Housings](#) category:*

*Click to view products by [CONEC](#) manufacturer:*

Other Similar products are found below :

[892-18-020-10-001101](#) [58102-G61-06LF](#) [582553-1](#) [0009485154](#) [009176003701906](#) [0050291907](#) [LY20-4P-DT1-P1E-BR](#) [02.125.8002.8](#)  
[609-3404](#) [61062-3](#) [61082-181009](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [641991-4](#) [644827-2](#) [65817-010LF](#) [65817-015LF](#) [65863-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68645-018](#) [68648-049](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5020](#) [707-5028](#) [71.350.2428.0](#) [71918-208LF](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [787-8014-00](#) [79531-3000](#)  
[FCN-360C032-B](#) [FCN-367T-T012/H](#) [FCN-723D010/2](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#)