

ADA Series

Special attachment for installation of ADA Series is prepared.

Installation attachment type	Model
F-ADA-1	ADA Series
F-ADA-2	ADA Series
F-ADA-3	ADA Series
F-ADA-4	ADA Series
F-ADA-5	ADA600F

★Refer to Instruction Manual 2.3 for installation A, B and C.

F-ADA-1	F-ADA-2	F-ADA-3
<p>★ Material: SPCC t=2.0 ★ Weight : 35g max</p>	<p>★ Material: SPCC t=2.0 ★ Weight : 45g max</p>	<p>★ Material: SPCC t=2.0 ★ Weight : 55g max</p>

★ M4 screw is requested when mounting. Please check the instruction manual for the size of screw.

<p>① It is use in accordance with installation B.</p>	<p>② It is use in accordance with installation A.</p>	<p>① Using hole-A It is use in accordance with installation B.</p>	<p>② Using hole-B It is use in accordance with installation A.</p>	<p>It is possible to comply with installation A because the space is kept by 30mm.</p>
---	---	--	--	--

F-ADA-4	F-ADA-5
<p>★ Material: SPCC t=2.0 ★ Weight : 20g max</p>	<p>★ Material: SPCC t=2.0 ★ Weight : 80g max</p>

★ M4 screw is requested when mounting. Please check the instruction manual for the size of screw.

<p>It is use in accordance with installation C. It is possible to comply with installation A or B when the power supply is vertically installed.</p>	<p>It is possible to install from the rear, and to use from the front. (Only ADA600F)</p>
--	---

Harness to use the function of ADA Series is prepared.

* Please see the our company home page or consult us about detailed information.

ADA Series

Mating harness

Model	Harness model #	Contents
ADA Series	H-SN-23	:Harness for using option:-W and/or -R when I/O interface is terminal block type (standard).
	H-IN-11	:Input harness when I/O interface is connector type (option:-J).
	H-OU-26	:Output harness when I/O interface is connector type (option:-J).
	H-PA-5	:Harness for parallel operation when I/O interface is connector type (option:-J).
	H-RC-2	:Harness for using option:-R when I/O interface is connector type (option:-J).

●Model number
H-SN-23

Housing : PHDR-14VS(J.S.T)
Pin : SPHD-002T-P0.5(J.S.T)
Weight : 6g max

●Type

●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1061	28	red	500
2	UL1061	28	black	500
3	-	-	-	-
4	-	-	-	-
5	-	-	-	-
6	-	-	-	-
7	-	-	-	-
8	-	-	-	-
9	UL1061	28	orange	500
10	UL1061	28	blue	500
11	-	-	-	-
12	-	-	-	-
13	UL1061	28	yellow	500
14	UL1061	28	black	500

* Even number pin side of the connector is the same wiring as odd number pin side.

●Model number
H-IN-11

Housing : 1-178129-6(AMP)
Pin : 1-175218-5 equivalent goods(AMP)
Weight : 45g max

●Type

●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
B 1	UL1051	18	white	500
A 1	UL1051	18	white	500
B 2	-	-	-	-
A 2	-	-	-	-
B 3	UL1051	18	black	500
A 3	UL1051	18	black	500

●Model number
H-OU-26

Housing : 178289-5(AMP)
Pin : 1-353717-5 equivalent goods(AMP)
Weight : 105g max

●Type

●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
B 1	UL1007	16	red	500
A 1	UL1007	16	red	500
B 2	UL1007	16	red	500
A 2	UL1007	16	red	500
B 3	UL1007	16	red	500
A 3	UL1007	16	black	500
B 4	UL1007	16	black	500
A 4	UL1007	16	black	500
B 5	UL1007	16	black	500
A 5	UL1007	16	black	500

●Model number
H-PA-5

Housing : 171822-2(AMP)
Pin : 170204-2 equivalent goods(AMP)
Weight : 4g max

●Type

●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1007	22	white	200
2	UL1007	22	black	200

●Model number
H-RC-2

Housing : 171822-3(AMP)
Pin : 170204-2 equivalent goods(AMP)
Weight : 7g max

●Type

●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1007	22	white	500
2	-	-	-	-
3	UL1007	22	red	500

July 20, 2020

Option-29

■ Fan unit

ADA Series

Fan unit type	Matching model	External	Harness								
FAN-AD6-24	ADA600F-24	<p>Air flow</p> <p>★Weight : 230g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD6-48	ADA600F-30 ADA600F-36 ADA600F-48	<p>Air flow</p> <p>★Weight : 220g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD7-24	ADA750F-24	<p>Air flow</p> <p>★Weight : 230g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD7-48	ADA750F-30 ADA750F-36 ADA750F-48	<p>Air flow</p> <p>★Weight : 220g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD1-24	ADA1000F-24	<p>Air flow</p> <p>★Weight : 450g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD1-48	ADA1000F-30 ADA1000F-36 ADA1000F-48	<p>Air flow</p> <p>★Weight : 420g max</p>	<table border="1"> <tr><td colspan="2">Wire</td></tr> <tr><td>Color</td><td>Content</td></tr> <tr><td>red</td><td>POWER</td></tr> <tr><td>black</td><td>GND</td></tr> </table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										

- * 1 Handle with care and don't add the impact such as falls or throwing to the unit.
- * 2 Exchange the unit after intercepting the input power.
- * 3 When the unit is exchanged, make sure there are not loosening of terminal screw and shutting the harness.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [DC Fans](#) category:

Click to view products by [Cosel](#) manufacturer:

Other Similar products are found below :

[614R](#) [AUB0612L](#) [AFB0948HH-S687](#) [G2E085-AA05-10](#) [4318/12T](#) [AUB0912H-F00](#) [3412N/2ME](#) [W2G110-AM39-01](#) [8412GLV](#) [8412NGL-12](#) [6448-384](#) [4114N/17-251](#) [4318/2R](#) [4412F/2D](#) [424JMU](#) [4414/2HH](#) [4112 N/12GL-175](#) [9GA0912F402](#) [9GA0812B20011](#)
[AFB0824SHBAV1](#) [DV5214/2NP-230](#) [9GA0912H4021](#) [THC1548MGDJJ](#) [9GA0812B2001](#) [GFB1224SHG](#) [8500NU](#) [9WG1212E101-E](#)
[3241.124](#) [DC0401012V2B-3T0](#) [ASFP14391](#) [ASFP64371](#) [ASFP64391](#) [ASFP84391](#) [ASFP92391](#) [9A0612G402](#) [AD5012HB-C71](#)
[AD5012MB-C71](#) [ASFP84372](#) [ASFP64372](#) [31100-000440-RS](#) [026758A](#) [514F](#) [MEC0381V1-000U-G99](#) [4292](#) [MF60152V1-1000U-G99](#)
[3610KL-04W-B50-D00](#) [109P0412K3023](#) [EE92251B1-000U-F99](#) [8218J/2H4P](#) [PF60381B1-000U-S99](#)