

ADA Series

Special attachment for installation of ADA Series is prepared.

Installation attachment type	Model
F-ADA-1	ADA Series
F-ADA-2	ADA Series
F-ADA-3	ADA Series
F-ADA-4	ADA Series
F-ADA-5	ADA600F

★Refer to Instruction Manual 2.3 for installation A, B and C.

<p>F-ADA-1</p> <p>★ Material: SPCC t=2.0 ★ Weight : 35g max</p>	<p>F-ADA-2</p> <p>★ Material: SPCC t=2.0 ★ Weight : 45g max</p>	<p>F-ADA-3</p> <p>★ Material: SPCC t=2.0 ★ Weight : 55g max</p>
<p>★ M4 screw is requested when mounting. Please check the instruction manual for the size of screw.</p>		
<p>① It is use in accordance with installation B. ② It is use in accordance with installation A.</p>	<p>① Using hole-A It is use in accordance with installation B. ② Using hole-B It is use in accordance with installation A.</p>	<p>It is possible to comply with installation A because the space is kept by 30mm.</p>
<p>F-ADA-4</p> <p>★ Material: SPCC t=2.0 ★ Weight : 20g max</p>	<p>F-ADA-5</p> <p>★ Material: SPCC t=2.0 ★ Weight : 80g max</p>	
<p>★ M4 screw is requested when mounting. Please check the instruction manual for the size of screw.</p>		
<p>It is use in accordance with installation C. It is possible to comply with installation A or B when the power supply is vertically installed.</p>	<p>It is possible to install from the rear, and to use from the front. (Only ADA600F)</p>	

Harness to use the function of ADA Series is prepared.

* Please see the our company home page or consult us about detailed information.

ADA Series

Mating harness


Model	Harness model #	Contents
ADA Series	H-SN-23	:Harness for using option:-W and/or -R when I/O interface is terminal block type (standard).
	H-IN-11	:Input harness when I/O interface is connector type (option:-J).
	H-OU-26	:Output harness when I/O interface is connector type (option:-J).
	H-PA-5	:Harness for parallel operation when I/O interface is connector type (option:-J).
	H-RC-2	:Harness for using option:-R when I/O interface is connector type (option:-J).

●Model number

H-SN-23

Housing : PHDR-14VS(J.S.T)
Pin : SPHD-002T-P0.5(J.S.T)
Weight : 6g max

●Type



●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1061	28	red	500
2	UL1061	28	black	500
3	-	-	-	-
4	-	-	-	-
5	-	-	-	-
6	-	-	-	-
7	-	-	-	-
8	-	-	-	-
9	UL1061	28	orange	500
10	UL1061	28	blue	500
11	-	-	-	-
12	-	-	-	-
13	UL1061	28	yellow	500
14	UL1061	28	black	500


* Even number pin side of the connector is the same wiring as odd number pin side.

●Model number

H-IN-11

Housing : 1-178129-6(AMP)
Pin : 1-175218-5 equivalent goods(AMP)
Weight : 45g max

●Type



●Wire


Pin #	Wire	AWG	Color	Length ℓ (mm)
B 1	UL1051	18	white	500
A 1	UL1051	18	white	500
B 2	-	-	-	-
A 2	-	-	-	-
B 3	UL1051	18	black	500
A 3	UL1051	18	black	500

●Model number

H-OU-26

Housing : 178289-5(AMP)
Pin : 1-353717-5 equivalent goods(AMP)
Weight : 105g max

●Type



●Wire


Pin #	Wire	AWG	Color	Length ℓ (mm)
B 1	UL1007	16	red	500
A 1	UL1007	16	red	500
B 2	UL1007	16	red	500
A 2	UL1007	16	red	500
B 3	UL1007	16	red	500
A 3	UL1007	16	black	500
B 4	UL1007	16	black	500
A 4	UL1007	16	black	500
B 5	UL1007	16	black	500
A 5	UL1007	16	black	500

●Model number

H-PA-5

Housing : 171822-2(AMP)
Pin : 170204-2 equivalent goods(AMP)
Weight : 4g max

●Type



●Wire


Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1007	22	white	200
2	UL1007	22	black	200

●Model number

H-RC-2

Housing : 171822-3(AMP)
Pin : 170204-2 equivalent goods(AMP)
Weight : 7g max

●Type









●Wire

Pin #	Wire	AWG	Color	Length ℓ (mm)
1	UL1007	22	white	500
2	-	-	-	-
3	UL1007	22	red	500

Fan unit

ADA Series

Fan unit type	Matching model	External	Harness								
FAN-AD6-24	ADA600F-24	<div><div>Air flow</div><div></div><div>★Weight : 230g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD6-48	ADA600F-30 ADA600F-36 ADA600F-48	<div><div>Air flow</div><div></div><div>★Weight : 220g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD7-24	ADA750F-24	<div><div>Air flow</div><div></div><div>★Weight : 230g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD7-48	ADA750F-30 ADA750F-36 ADA750F-48	<div><div>Air flow</div><div></div><div>★Weight : 220g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD1-24	ADA1000F-24	<div><div>Air flow</div><div></div><div>★Weight : 450g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										
FAN-AD1-48	ADA1000F-30 ADA1000F-36 ADA1000F-48	<div><div>Air flow</div><div></div><div>★Weight : 420g max</div></div>	<table><tr><th colspan="2">Wire</th></tr><tr><th>Color</th><th>Content</th></tr><tr><td>red</td><td>POWER</td></tr><tr><td>black</td><td>GND</td></tr></table>	Wire		Color	Content	red	POWER	black	GND
Wire											
Color	Content										
red	POWER										
black	GND										

★ 1 Handle with care and don't add the impact such as falls or throwing to the unit.

★ 2 Exchange the unit after intercepting the input power.

★ 3 When the unit is exchanged, make sure there are not loosening of terminal screw and shutting the harness.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Fan Accessories](#) category:

Click to view products by [Cosel](#) manufacturer:

Other Similar products are found below :

[LZ31](#) [LZ32P-1](#) [63070-2-4013](#) [64442-1-7612](#) [71882-2-4053](#) [73816-2-3634](#) [95778-1-5171](#) [99485901](#) [1247-4-6254](#) [RF119](#) [2151-4-7320](#)
[27453.32262](#) [95779-1-5171](#) [9614-2-4013](#) [99485906](#) [F92-B](#) [2170-4-7320](#) [27453.32241](#) [R88ACPU001M1](#) [R88ACPU001M2](#) [31570-2-4013](#)
[LZ215](#) [LZ22-2](#) [LZ24-1](#) [LZ24B](#) [LZ30-9](#) [LZ37-2](#) [450-20-0025](#) [525-00-0009](#) [420-05-0276](#) [450-20-0017](#) [450-20-0020](#) [04.846.1353.0](#)
[04.846.1453.0](#) [055032](#) [08121](#) [08188](#) [08195](#) [08196](#) [09576-2-4013](#) [54476-2-4013](#) [71883-2-4053](#) [52545-2-4037](#) [63071-2-4013](#) [52544-2-4037](#)
[64445-1-7612](#) [66786-4-7320](#) [88601-2-2929](#) [08164](#) [4013-2-4039](#)