



PCB Layout

$$A = 2.0 * \frac{nP}{2} \pm 0.40$$

$$B = 2.0 * \frac{nP}{2} - 2.0 \pm 0.20$$
 Pin Number=2~80

Technical Data
 Material: Brass
 Contact material: Brass
 Plating: Gold Flash
 Insulator material: Black polyester UL94V-0
 Standard: 6T+30%G.F

Electrical:
 Current rating: 1.5Amps/contact max.
 Contact resistance: $\leq 20m\Omega$ /contact
 Insulation resistance: $\geq 1000M\Omega$ at V=100V
 Withstanding voltage: 450V AC/minute

Mechanical:
 Soldering temperature: $+260^{\circ}C$, 4s max
 UNSPECIFIED TOLERANCE: ± 0.20



APPROVALS		DATE	DRAWING NO.																	
DRAWN	G.M.Chen	2015/7/17	D/2200W-22-XX-52																	
CHECKED			SHEET 1 OF 1																	
APPROVALS			PROJ.																	
TOLERANCES ARE: <table border="1" style="display: inline-table; margin-left: 10px;"> <tr> <td>30~80 ±</td> <td>±0.30</td> <td>ANGLE</td> <td>±2°</td> </tr> <tr> <td>10~30</td> <td>±0.20</td> <td>UNIT:</td> <td>mm</td> </tr> <tr> <td>5~10</td> <td>±0.15</td> <td>SCALE:</td> <td>1:1</td> </tr> <tr> <td>~5</td> <td>±0.10</td> <td></td> <td></td> </tr> </table>					30~80 ±	±0.30	ANGLE	±2°	10~30	±0.20	UNIT:	mm	5~10	±0.15	SCALE:	1:1	~5	±0.10		
30~80 ±	±0.30	ANGLE	±2°																	
10~30	±0.20	UNIT:	mm																	
5~10	±0.15	SCALE:	1:1																	
~5	±0.10																			
ECN NO.	REV.	DATE.	DESCRIPTION.	CHANGE.	CHECK.	APPRO.														
	A		NEW																	



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [DEALON](#) manufacturer:

Other Similar products are found below :

[0015917161](#) [0022155065](#) [57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [71.350.2428.0](#) [733-134](#) [733-162](#) [760-3052](#) [MHR-64-VUAL](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [801-43-002-10-013000](#)
[801-43-006-10-002000](#) [803-43-024-10-001000](#) [803-93-012-10-001000](#) [8-1437020-4](#) [819-22-004-30-001101](#) [820-22-006-30-001101](#)
[820-22-008-30-001101](#) [821-22-002-10-001101](#)