



- A. Underwriters Laboratory Listing 90P1C.
- B. Compatible with [Desco Dual-Wire Continuous Monitors](#) and other brands that accept a [3.5mm phono plug](#).
- C. Desco logo molded in compliance with ANSI/ESD S1.1.
- D. Thermoplastic elastomer strain relief [molded](#) on.
- E. Relaxed retraction coil cord reduces tug on wearer's wrist. Black PVC insulation. Break load average 30 pounds.
- F. Dual T-3067 tinsel conductor. Consists of stranded polyester wrapped in copper. Equivalent to 29 gauge (cir mil and/or ohms).
- G. 1 megohm ($\pm 5\%$) current limiting resistors on both conductors.
- H. Unique dual contact design is to be paired with a [Desco MagSnap 360™ Wristband](#) (not included) for a superior electrical connection. The magnetic connection made with the wristband maintains a 1-5 pound perpendicular breakaway force to prevent accidental disconnects. Spring loaded center contact rated to 1 million cycles.
- I. Date coded with date of manufacture in compliance with ANSI/ESD S1.1.

Meets required limits of ANSI/ESD S20.20 and requirements of ANSI/ESD S1.1.

Item	Mold Color	Mono Plug Tip Diameter	Retracted Length		Extended Length	
			X	Y	Nominal	Max
19880	Black	0.132"	12"	20"	6'	8.5'
19881	Black	0.132"	24"	32"	12'	17'
19882	Black	0.132"	30"	38"	15'	22'
19877	Grey	0.116"	12"	20"	6'	8.5'
19878	Grey	0.116"	24"	32"	12'	17'
19879	Grey	0.116"	30"	38"	20'	22'

U.S. Patent Pending

Unless otherwise noted, tolerance $\pm 10\%$

Specifications and procedures subject to change without notice.

MAGSNAP 360™ DUAL-WIRE COIL CORD

DESCO WEST: 3651 WALNUT AVE, CHINO, CA 91710 WEBSITE: Desco.com
PHONE: (909) 627-8178

DESCO EAST: ONE COLGATE WAY, CANTON, MA 02021-1407
PHONE: (781) 821-8370

DRAWING NUMBER
19880

DATE
January 2015



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Antistatic Control Products](#) category:

Click to view products by [Desco](#) manufacturer:

Other Similar products are found below :

[13020](#) [13490](#) [13870](#) [13879](#) [13881](#) [13883](#) [13882](#) [14404](#) [2202SP](#) [3039](#) [37061](#) [42470](#) [09060](#) [09857](#) [42516](#) [37059](#) [04563](#) [17252](#) [19691](#)
[19695](#) [09037](#) [09826](#) [09813](#) [66070](#) [100816](#) [68101](#) [68103](#) [98132](#) [73741](#) [13868](#) [13485](#) [13457](#) [13245](#) [13468](#) [13420](#) [13332](#) [13205](#) [13135](#)
[91070](#) [8031](#) [8523](#) [66085](#) [40931](#) [37081](#) [13080](#) [13215](#) [13806](#) [73749](#) [010-0225](#) [17260](#)