



**T-3 1/4 Based LED Cluster Replacement Lamps – Bayonet Base**

PART NO.	COLOR	PEAK WAVELENGTH nm	NOMINAL VOLTAGE	FORWARD CURRENT mA Typ	INTENSITY mcd	
					Min	Typ
585-5211	Ultra Red	660	6	60	114	480
585-5411	Yellow	585	6	60	114	420
585-5511	Bright Yellow	592	6	90	315	1800
585-5311	Green	565	6	60	114	420
585-52x3*	Ultra Red	660	14	40	114	480
585-54x3*	Yellow	525	14	40	114	420
585-55x3*	Bright Yellow	592	14	60	315	1800
585-53x3*	Green	565	14	40	114	420
585-52x5*	Ultra Red	660	28	20	133	560
585-54x5*	Yellow	585	28	20	133	490
585-55x5*	Bright Yellow	592	28	30	367	2100
585-53x5*	Green	565	28	20	133	490
585-5256	Ultra Red	660	120VAC	9	60	252
585-5456	Yellow	585	120VAC	9	60	220
585-5556	Bright Yellow	592	120VAC	9	165	945
585-5356	Green	565	120VAC	9	60	220



†PART NUMBER ORDERING CODE  
**585 - 5xxx**  
 †Series †Polarity Options  
 1 = Polarized  
 2 = Bi-Polar (polarity insensitive)  
 Note: Bi-polar option not available for 6 volt devices.  
 120VAC device do not apply.

Replaces incandescent lamp numbers - for example: 44, 47, 313, 755, 757, 1815, 1819, 1847, 1866, 1889, 1891, 1892, 1893 and 1895. For more information, please contact factory.

\* Electrical specifications shown are for polarized devices. Non-polarized devices will vary slightly.

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Dialight](#) manufacturer:*

Other Similar products are found below :

[004-1830-29-201](#) [004-1830-29-207](#) [004-1930-29-203](#) [004-1930-29-207](#) [0042900300](#) [008-0000-948](#) [008-0111-200](#) [008-0112-203](#) [008-0132-200](#) [008-0133-200](#) [019-0410-05-301](#) [019-0511-303](#) [019-0531-303](#) [019-0532-303](#) [019-0533-300](#) [019-0533-303](#) [019-0534-300](#) [019-0535-200](#) [0190535300](#) [019-0535-303](#) [019-0901-05-301](#) [019310105301](#) [019-3202-05-301](#) [019-3202-05-303](#) [019-3206-05-303](#) [019-3402-05-203](#) [021-0410-2900-301](#) [021041029301](#) [021-1310-2900-301](#) [021-1310-29-201](#) [021-1310-29-301](#) [021-2900-200](#) [021-2900-300](#) [026-0410-11-301](#) [026-1111-200](#) [026-1111-203](#) [026-1111-300](#) [026-1112-203](#) [026-1112-300](#) [026-1113-203](#) [026-1131-203](#) [026-1131-300](#) [0261131303](#) [026-1132-203](#) [026-1132-300](#) [026-1132-303](#) [026-1133-203](#) [026-1133-300](#) [026-1134-300](#) [026-1135-203](#)