EAO – Your Expert Partner for **Human Machine Interfaces**

10-4H21.1034P - Multi-LED Fail Safe

10-4H21.1034P - Multi-LED Fail Safe



Attention: The preview is based on a sample product. This can differ from your current configuration.

Other Attributes

 Weight
 0,002 kg

 Operation current
 2,2 mA -30%/+25%

 Operating voltage
 72 V AC/DC -30%/+25%

Illumination

Socket BA9s LED colour Multi-LED yellow

Optics

Lumi. intensity 4 x 112 mcd Dom. wavelength 589 nm


e a o

Stand: 12.09.2019


EAO – Your Expert Partner for **Human Machine Interfaces**

10-4H21.1034P - Multi-LED Fail Safe

Dimensions



Wiring diagram



Additional information

rectifier

The max. overall length of the lamp may not exceed 25mm Electrical and optical data are measured at 25 $^{\circ}\text{C}$ The specified 72 and 110 VAC/VDC versions are built with a

protection diode
Specified 72 and 110 VAC/VDC versions are built with a bridge

In case one LED fails, the other pair of still functioning LED's is working. The light output then is half in order to indicate the malfunction and shows this way the need for replacement Luminosity and wave length variations caused by LED manufacturing processes may cause slight differences regarding the illumination

eao 🔳

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Industrial Panel Mount Indicators / Switch Indicators category:

Click to view products by EAO manufacturer:

Other Similar products are found below:

LW1A-P1-GD LW1A-P1-W 01-931.3 01-152.025 73.362.4028.0 750-1520 9001OA120 A0142N5 A3DT-500Y AL6M-LK3-R AL6M-P7P-A AOLQW-2B0600 AP1M255-A APD106LN-G APD106LN-S APN1126-G APS122DN-W ASLWLD-G ASLWLD-R ATN2100 AYLW4L-A 18-237.035 18-945 HW1A-L1-GD HW1A-P2-GL HW1X-BM411-R HW2A-L1-GL HWAZ1N-OB PA2100/2 PA2200/1 PA2SHIELD PAMR25 LA3P-1C03V-Y 96-923.5 A0244J2 LSPD-120A LSPD-1Y LSPD-6A LSPD-6DA LSPD-6DW LSPD-6DY LSPD-6R LSPD-6W 18-946 AL6H-LK3-A AL6H-P4-JW AL6M-LK1-MG AP8M155-G APD106LN-W APN106L-O