



**EAO AG**

Tannwaldstrasse 88

4600 Olten

Switzerland

**Phone:** +41 62 286 9111

[info@eao.com](mailto:info@eao.com)

## Part No. 45-1131.1140.000.101, Pushbutton



[Specifications](#) | [Bill of Materials](#)

### Specifications

<b>Actuator</b>	<u>Pushbutton</u>
<b>Lens Colour</b>	Yellow
<b>Function</b>	2 Positions, momentary (O<I)
<b>Housing Material</b>	Plastic
<b>Shape of Handle or Frontring</b>	raised/ level to bezel
<b>Lock System</b>	None
<b>Key</b>	None
<b>Key Type</b>	None
<b>Switching Angle</b>	None
<b>Contacts</b>	1NO
<b>Terminal</b>	Screw terminal
<b>Voltage Illumination</b>	None

<b>Mounting Type</b>	Front mounting
<b>Mounting Style</b>	Holder
<b>Environmental Rating</b>	IP66, IP67, IP69K
<b>Industry Standards/Certifications</b>	UL, CSA, VDE, CCC, CE, RoHS
<b>Switching Function</b>	On-Off
<b>Illumination</b>	None
<b>Contact Material</b>	Silver
<b>Termination Style</b>	Screw
<b>Mechanical Life</b>	Maintain 500'000 switching cycles Momentary 10'000'000 switching cycles
<b>AC Voltage</b>	500 V
<b>DC Voltage</b>	500 V
<b>Switching Current</b>	10 A

Bill of Materials -

<b>Actuator</b>	45-2131.1140.000
<b>Holder</b>	45-2300.1000.000
<b>Switch Element 1</b>	45-311.1Z10

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Pushbutton Switches](#) category:*

*Click to view products by [EAO](#) manufacturer:*

Other Similar products are found below :

[8971K1133](#) [LW1L-M1C10V-A](#) [LW2L-M1C20M-A](#) [M22-D-R-GB0/K11](#) [701PB580](#) [7199K101](#) [810K12910](#) [810KSV30B](#) [FLT 2U EE 01A](#)  
[MML21EA2ADK](#) [MML21KA3ABK](#) [MML23KA3AC05K-001](#) [MML23KW3AA01W](#) [8418K2](#) [8442K3](#) [8450K1](#) [860K11911T01A](#) [861901](#)  
[861K11911T01A07](#) [861K13810T00A14](#) [861K13911](#) [8646AB6X718UL](#) [8646ABUL](#) [9533CD4+U574+U4922](#) [95-414.000](#) [99-453.837](#)  
[A2PMA1X03EC56](#) [A3A-7310](#) [A3A-7340](#) [12037A2ULCSA](#) [1203A2UL](#) [ABGW410-R](#) [1211390004](#) [ABN400-R](#) [121382](#) [1213C3](#) [HE3B-M2](#)  
[1211500044](#) [121194](#) [1212MRA](#) [1241.1183.7047](#) [121489](#) [1223A2ULCSA](#) [1241.1183.8000](#) [1241.1183.8029](#) [D5P-MT4](#) [13435AG](#)  
[13445AD29GX768](#) [AG23-L2](#) [AH165-2SGLG1TE3](#)