



Eaton TVS diode ESD suppressors: selection and sizes

Package size	Family	Reverse working voltage	ESD withstand range	Peak pulse current (8/20 μs)	Capacitance range
DFN0603	STN061050B300	5.0 V	30 kV	Up to 7A	4 pF
	STN06XXXB101	3.3 V to 5.0 V	30 kV	Up to 7 A	10 pF
	STN06XXXBL15	3.3 V to 5.0 V	15 kV	Up to 4 A	0.15 pF
	STN061050BL40	5.0 V	18 kV to 20 kV	Up to 5 A	0.4 pF
DFN1006	STN10XXXXLXX	5.0 V	15 kV	Up 5 A	0.8 pF to 0.9 pF
	STN101XXBXXX	3.3 V to 12 V	30 kV	Up to 8 A	10 pF to 11 pF
	STN101050B301	5.0 V	30 kV	Up to 20 A	30 pF
	STN101050BL30	5.0 V	20 kV	Up to 4.5 A	0.3 pF
	STN101050BL25	5.0 V	25 kV	Up to 5 A	.25 pF
DFN1610	STN161XXXUXXX	5.0 V to 15 V	30 kV	Up to 110 A	330 pF to 850 pF
DFN2x2	STN202XXXUXXX	7.5 V to 24 V	30 kV	Up to 240 A	750 pF to 1700 pF
DFN2010	STN204033BL60	3.3 V	30 kV	Up to 20 A	1.0 pF
DFN2510	STN254033UL33 & STN254033UL50	3.3 V	15 kV	Up to 3 A	0.2 pF to 0.5 pF
	STN254050UL50 & STN254050UL50H	5.0 V	15 kV to 20 kV	Up to 5 A	0.25 pF to 0.5 pF
	STN265033U380	3.3 V	30 kV	Up to 25 A	2 pF to 3.8 pF
SOT23-6L	STS234XXXUXXX	3.3 V to 5.0 V	20 kV to 30 kV	Up to 24 A	0.3 pF to 3 pF
SOD-523	STS521XXXUXXX	3.3 V to 36 V	15 kV to 30 kV	Up to 10 A	16 pF to 110 pF
	STS521XXXBXXX	3.3 V to 5.0 V	8 kV to 30 kV	Up to 20 A	0.9 pF to 95 pF
SOD-323	STS32XXXUXXX	5.0 V to 15 V	30 kV	Up to 110 A	330 pF to 850 pF
	STS321XXXBXX0	3.3 V to 24 V	30 kV	Up to 20 A	1 pF
	STS321XXXBXX1	3.3 V to 36 V	30 kV	Up to 30 A	14 pF to 40 pF
	STS321XXXUXXX	3.3 V to 36 V	8 kV to 30 kV	Up to 25 A	35 pF to 200 pF
	STS321045B502	4.5 V	30 kV	Up to 140 A	450 pF
SOT23	STS232033U202	3.3 V	15 kV	Up to 25 A	200 pF
	STS232050UL40	5.0 V	20 kV	Up to 4 A	0.2 pF to 0.4 pF
	STS232120U901	12 V	30 kV	Up to 20 A	45 pF to 90 pF
	STS232712B451	7.0 V to 12 V	15 kV	Up to 12 A	45 pF to 75 pF
	STS232XXXUXXX	3.3 V to 36 V	15 kV	Up to 18 A	26 pF to 150 pF
	STS232XXXBXXX	3.3 V to 36 V	15 kV to 30 kV	Up to 20 A	15 pF to 100 pF
SOT-143	STS142XXXUXXX	5.0 V to 70 V	20 kV to 30 kV	Up to 24 A	0.4 pF to 0.8 pF
SOP-8	STSP84XXXXXX	2.8 V to 15 V	15 kV to 30 kV	Up to 12 A	0.65 pF to 60 pF

Eaton
Electronics Division
 1000 Eaton Boulevard
 Cleveland, OH 44122
 United States
 Eaton.com/electronics

© 2021 Eaton
 All Rights Reserved
 Printed in USA
 Publication No. 11009 BU-MC19136
 June 2021

Eaton is a registered trademark.

All other trademarks are property of their respective owners.

Follow us on social media to get the latest product and support information.



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [ESD Suppressors / TVS Diodes](#) category:

Click to view products by [Eaton](#) manufacturer:

Other Similar products are found below :

[60KS200C](#) [D12V0H1U2WS-7](#) [D18V0L1B2LP-7B](#) [82356050220](#) [D5V0M5U6V-7](#) [NTE4902](#) [P4KE27CA](#) [P6KE11CA](#) [P6KE39CA-TP](#)
[P6KE8.2A](#) [SA110CA](#) [SA60CA](#) [SA64CA](#) [SMBJ12CATR](#) [SMBJ8.0A](#) [SMLJ30CA-TP](#) [ESD101-B1-02ELS E6327](#) [ESD112-B1-02EL E6327](#)
[ESD119B1W01005E6327XTSA1](#) [ESD5V0L1B02VH6327XTSA1](#) [ESD7451N2T5G](#) [19180-510](#) [CPDT-5V0USP-HF](#) [3.0SMCJ33CA-F](#)
[3.0SMCJ36A-F](#) [HSPC16701B02TP](#) [D3V3Q1B2DLP3-7](#) [D55V0M1B2WS-7](#) [DESD5V0U1BL-7B](#) [DRTR5V0U4SL-7](#) [SCM1293A-04SO](#)
[ESD200-B1-CSP0201 E6327](#) [ESD203-B1-02EL E6327](#) [SM12-7](#) [SMF8.0A-TP](#) [SMLJ45CA-TP](#) [CEN955 W/DATA](#) [82350120560](#)
[82356240030](#) [VESD12A1A-HD1-GS08](#) [CPDUR5V0R-HF](#) [CPDUR24V-HF](#) [CPDQC5V0U-HF](#) [CPDQC5V0USP-HF](#) [CPDQC5V0-HF](#)
[D1213A-01LP4-7B](#) [D1213A-02WL-7](#) [ESDLIN1524BJ-HQ](#) [5KP100A](#) [5KP15A](#)