

**MKS1TM-10**

<b>Operational Frequency</b>		50-60 Hz
<b>Product</b>		Motor Protection Switch
<b>Current</b>	<b>Ie</b>	25 A
<b>Thermic Current</b>		6,30-10,0A
<b>Calibration Interval</b>		
<b>Usage Category</b>		AC 3
<b>Mechanical Life</b>	<b>Min Qty</b>	100000
<b>Electrical Life</b>	<b>Min Qty</b>	100000
<b>Operating Frequency</b>	<b>On-Off/Hour</b>	Mek. 360 Elk. 360
<b>Insulation Voltage</b>	<b>Ui</b>	690V AC
<b>Impulse Withstand Voltage</b>	<b>Uimp</b>	6 kV
<b>Dielectric Strength (Contact-Contact)</b>		1890V
<b>Isolation Resistance</b>		10 MΩ Min. (500 V DC)
<b>Operating Temperature</b>		-5 / +40 °C
<b>Pollution Degree</b>		3
<b>Protection Degree</b>		IP40
<b>Cable Section</b>		0,75-4 mm <sup>2</sup>
<b>Screw Torque</b>		1,8 Nm
<b>Short Circuit Breaking Capacity</b>	<b>Ics</b>	6 kA
<b>Production Time</b>		Adjustable overload release 13 ranges between 0.1-25 A; Short circuit release factor set at 12xIe; Short circuit switching capacity minimum 6 kA / 400 V
<b>Serial Specifications</b>		MKS Series Adjustable overload release 13 ranges between 0.1-25 A Short circuit release factor set at 12xIe Short circuit switching capacity minimum 6 kA / 400 V
<b>Standards / Certificates</b>		TS EN 60947-4-1

CE

ERT



TSE

UK  
PA

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Contactors - Electromechanical category](#):*

*Click to view products by [EMAS manufacturer](#):*

Other Similar products are found below :

[686-120111](#) [70-901](#) [70-914](#) [MB-3D-6](#) [MC-22A/4-AC120V](#) [8-1616943-9](#) [8-1672124-5](#) [A701U](#) [AVR743D](#) [B6-40-00-84](#) [B7-40-00-84](#)  
[1616017-5](#) [HP-11D-24](#) [P25-E5019-1](#) [P40P47D13P1-24-01](#) [CA7-72-00-24Z](#) [90-162](#) [9-1393132-2](#) [2NC4F0222](#) [ACC338UMM20](#)  
[AF80-30-11-13](#) [SZ-B1](#) [3GC2H0M22](#) [3NC0T0A22](#) [3NC1Q0A22](#) [42AF35AG](#) [42AF35AH](#) [42CF35AE](#) [42CF35AL](#) [42FE35AFR](#)  
[45CG10AFA](#) [45CG10AJA](#) [45CG10EJA](#) [45CG20AF](#) [45CG20AL](#) [45CG20EF](#) [45CG20EG](#) [45CG20EL](#) [45DG10AFA](#) [45DG10AGA](#)  
[45DG10AJA](#) [45DG10ALA](#) [45DG10ELA](#) [45DG20AG](#) [45DG20AL](#) [45EG10AFA](#) [45EG10AJA](#) [45EG10ALA](#) [45EG20AL](#) [45FG10AFA](#)