**Energizer** 

# **Product Image**



**Energizer** 

### **Product Description**

The Energizer HDL40 Waterproof, Dustproof, Multi-colored Headlamp is another innovative headlamp solution within the extensive headlamp line. Featuring bright, durable and energy efficient LED technology (12 X Brighter than Standard LED),, users get a bright, lightweight, hands-free solution with ample run time capability. It is a perfect light for home, work and outdoor activities. With the advanced dimming feature on all light settings, users can control the intensity of light from 100% to 10%. With a comfortable, adjustable head strap, anti-glare design, and pivoting head to direct light exactly as needed, this headlamp is another way *Energizer®* continues to deliver innovative lighting solutions.

### **DESIGN FEATURES AND BENEFITS**

- ✓ Red LED mode allows users to preserve night vision
- ✓ Compact, lightweight design with pivoting head
- ✓ Pivoting head to direct light where needed.
- ✓ Waterproof with shatter proof lens

### **PERFORMANCE FEATURES AND BENEFITS**

- ✓ Waterproof for use in all weather conditions.
- ✓ Dimmable switching on all modes allows users to control light intensity and manage battery life
- √ 4 modes to provides versatility to suit your needs
- ✓ Bright, durable, energy-efficient LED technology

	Modes and Features								
X	High Spot	High Flood (Wide)	Warm Mode	X Re	ed		Area High		
	Medium Spot	Medium Flood (Wide)	Cool Mode	X Re	ed Flashing		Area Medium		
Х	Low Spot	Low Flood (Wide)	Warm and Cool Together	G	ireen		Area Low		
	Ultra Low Spot	Emergency Strobe (>5hz see warning copy)			ireen lashing		Nightlight		
Х	Press and Hold Dimming	Safety Flashing <5Hz		SC	OS				

### **OPERATING INSTRUCTIONS**

- 1. Press right switch to turn on in High.
- 2. Press 2 times for Low.
- 3. Press and hold in any white light mode for dimming. Light will flash at highest and lowest settings. Release to set light level.
- 4. Press left button for Red modes.
- 5. Press 1 time for Red.
- 6. Press 2 times for Flashing Red.
- 7. After 2 seconds in any mode, next press will be off.

### **BATTERY CHANGING or CHARGING INSTRUCTIONS**

- 1. Lift latch to unlock battery door.
- 2. Open battery door and follow orientation instructions inside battery compartment to replace the batteries.
- 3. Close and press latch to lock.

## **BATTERY CHARGE INDICATOR**

# **Energizer HDL40 Headlamp**

# **Energizer**

	ANSI F	PERFORMANCE	DATA		
Lumens	Runtime	Beam Distance	Drop	Water Ingress	
500 LUMENS	FL1 STANDARD 3h	FL1 STANDARD	FL1 STANDARD 2m	FL1 STANDARD  1m  IPX7	
BATTERY PERFORMANCE					

PRODUCT SPECIFICATIONS								
Weight:	76		g	grams 2.7		ounce		unces
	Len	gth		Wie	dth		Hei	ght
Dimensions:	65.6 mr		n	47.1	mm	49	.3	mm
	2.6	Ir	1	1.9	In	1.	.9	in
Weight does not include user replaceable batteries (unless specified)								

BATTERY PERFORMANCE							
Battery Type ENR Max Alkaline							
Modes	Lumens (lm)	Runtime (h)	Beam Distance (m)				
High	500	3	75				
low	80	22	_				

BATTERY SPECIFICATIONS							
Quantity:	3	Size:	AAA	User Replaceable?	Yes		
Type:	Primary Cylindrical						

ELECTRICAL CHARACTERISTICS						
Nominal Power Consumption: 4.65 W						
Batteries:	3 AAA Energizer E92 4.5V dc					
<b>LED Specifications:</b> LED 3.0V cc / 1550 mA						

Contains magnets?	Shatterproof Lens:
No	Yes
LED CCT	LED CRI
5000K	70
Additional Ingress Protection	Other (Impact Testing, etc)
IP67	

**Energizer** 

## **Regulatory Information**

	CERTIFICATES AND COMPLIANCE									
	Global Certifications									
X	EMC EN62471 RoHS	Global								
Х	FCC	Tested on all product globally require	sted on all product globally required for USA only.							
	ASTM F963 Ages 3+	Global- All products marketed to children								
					Regional Certifications					
	RCM	Australia-Rechargeable products		NOM	Mexico—All Lights		CNS	Taiwan-All rechargeable products		
	EAC	EAC - Armenia, Belarus, Kazakhstan, Kyrgyzstan-Rechargeable products		InMetro	Brazil-AC Plug In Rechargeable		KC Mark	South Korea-All rechargeable products		
			1	UL/S Mark	Argentina-AC Plug In Rechargeable					
				Triman Logo	France—All lights					



### **REQUIRED REGULATORY INFO**

Tested according to ANSI FL1 Standards.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

### **PRODUCT WARNINGS and/or DISCLAIMERS**

Dept	Responsible	Approved for Publication	Date
Marketing	Miranda Phillips	YES	8/18/2022
Engineer	Bill Narpes	YES	8/18/2022
Regulatory	John Hadley	YES	8/18/2022
Legal	Jessica Mendez	Yes	9/01/2022
Substantiation Data	Ruth Sholtis-Furyes	Yes	9/6/2022

Versio n	Date Published	Published By	Description of Changes
1	9/1/2022	Ruth Sholtis-Furyes	Original PublicationDRAFT
2	9/6/2022	Ruth Sholtis-Furyes	IPX7 confirmed. Removed DRAFT.

## **X-ON Electronics**

Largest Supplier of Electrical and Electronic Components

Click to view similar products for Other Tools category:

Click to view products by Energizer manufacturer:

Other Similar products are found below:

899-2-KT46 568681-1 CR-12FP4--260R 5800-0090 58061-1 59085 00-8273-RDPP 593033 593072 593564100 593575 593593 0100003-0000 011349-000 CRCW08052740FRT1 LUC-012S070DSM LUC-018S070DSP LUC-024S105DSP 599-2021-3-NME 599-JJ-202103 CRCW2010331JR02 601-JJ-06 601-SPB 601YSY 602-JJ-03 602SPB 603-JJ-07-FP 603-JJY-04 CRTN1013 CS16 6-1579014-0 6203
6240-1 M43435 TY 1 SZ 3 FIN B BLK M43435 TY 2 SZ 3 FIN C BLK M-5Z M6816 660-29ABT1 662508-1 CVHD-950X-93.333
CW104-01X 671-GP-04-KT39-73207 CW307-01A CW30901A CW6211201A 679793-1 690191-1 690191-3 690317-2 691409-4