


KCS45 Tubular angle terminal

for multi-wire Cu cables



Material: galvanically tinned copper

Non tinned on request.

Cross section [mm ²]	For screw M	d ₂ [mm]	Symbol	s [mm]	d ₁ [mm]	d ₃ [mm]	a [mm]	l ₁ [mm]	l ₂ [mm]	Weight [g/pc]	Unit [pcs]	Dies discriminant	Crimping tools				
6	5	5,3	KCS45 5-6	1	4	9,5	9	8	8,5	3,90	10	6	EPZC300, EPZ300, GZ300, HRZ300, PRZ240, PR33, GO300, HR300, GU300, GU120, HR100-U, PR240, PR50, PP19, A11/6				
	6	6,4	KCS45 6-6											10	3,73		
10	5	5,3	KCS45 5-10	1,2	4,5	12	10	8	8,5	5,93	10	7	EPZC300, EPZ300, GZ300, HRZ300, PRZ240, GO300,				
	6	6,4	KCS45 6-10											12	7,5	8,5	6,14
	8	8,4	KCS45 8-10											13	10	11	6,60
16	6	6,4	KCS45 6-16	1,5	5,5	13	13	7,5	8,5	10,00	10	8	HR300, GU300, GU120, HR100-U, PR240, PR50, R50, PP19				
	8	8,4	KCS45 8-16											13	10	11	10,50
	10	10,5	KCS45 10-16											17	12	13	11,80
25	6	6,4	KCS45 6-25	1,5	7	14	15	7,5	8,5	14,00	10	10	PP19 + as below				
	8	8,4	KCS45 8-25											16	10	11	15,00
	10	10,5	KCS45 10-25											18	12	13	14,90
	12	13	KCS45 12-25											18	13	14	18,10
35	6	6,4	KCS45 6-35	1,75	8,5	17	17	7,5	8,5	22,30	10	12	EPZC300, EPZ300, GZ300, HRZ300, PRZ240, GO300,				
	8	8,4	KCS45 8-35											17	10	11	24,20
	10	10,5	KCS45 10-35											19	12	13	25,20
	12	13	KCS45 12-35											21	13	14	26,30
	14	15	KCS45 14-35											21	15,5	15,5	27,70
50	8	8,4	KCS45 8-50	2	10	20	19	10	11	33,20	10	14	HR300, GU300, GU120, HR100-U, PR240, PR120, PR150, PR50, PP19, A11/6				
	10	10,5	KCS45 10-50											20	12	13	34,60
	12	13	KCS45 12-50											23	13	14	33,30
	14	15	KCS45 14-50											23	15,5	15,5	39,10
	16	17	KCS45 16-50											28	16	17	43,20
70	8	8,4	KCS45 8-70	2,25	12	23,5	21	10	11	51,20	10	16	EPZC300, EPZ300,				
	10	10,5	KCS45 10-70											23,5	12	13	50,90
	12	13	KCS45 12-70											23,5	13	14	55,10
	14	15	KCS45 14-70											23,5	15,5	15,5	55,10
	16	17	KCS45 16-70											28	16	17	61,40
95	10	10,5	KCS45 10-95	2,25	13,5	26	25	12	13	58,612	10	18	GZ300, HRZ300, PRZ240, GO300, HR300, GU300, GU120, HR100-U, PR240, PR120, PR150				
	12	13	KCS45 12-95											26	13	14	59,11
	14	15	KCS45 14-95											26	15,5	15,5	67,90
	16	17	KCS45 16-95											28	16	17	69,00
	20	21	KCS45 20-95											34	19	20	74,00
120	10	10,5	KCS45 10-120	2,25	15,5	29	26	12	13	75,17	10	19	PR240, PR120, PR150				
	12	13	KCS45 12-120											29	13	14	76,40
	14	15	KCS45 14-120											29	15,5	15,5	87,60
	16	17	KCS45 16-120											30	16	17	88,90
	20	21	KCS45 20-120											36	19	20	89,56
150	10	10,5	KCS45 10-150	2,25	17	31	30	12	13	89,46	10	20	EPZC300, EPZ300, GZ300, HRZ300, PRZ240, GO300, HR300, GU300, PR240, PR150				
	12	13	KCS45 12-150											31	13	14	90,23
	14	15	KCS45 14-150											31	15,5	15,5	93,50
	16	17	KCS45 16-150											31	16	17	95,60
	20	21	KCS45 20-150											36	19	20	97,70
185	10	10,5	KCS45 10-185	2,5	19	35	30	12	13	115,00	10	23	PR240, PRZ240, + as below				
	12	13	KCS45 12-185											35	13	14	120,00
	14	15	KCS45 14-185											35	15,5	15,5	120,30
	16	17	KCS45 16-185											35	16	17	117,95
	20	21	KCS45 20-185											39	19	20	123,23
240	12	13	KCS45 12-240	2,5	21,5	39	35	13	14	140,00	10	25	EPZC300, EPZ300, GZ300, HRZ300, PRZ240, GO300, HR300, GU300				
	14	15	KCS45 14-240											39	15,5	15,5	145,10
	16	17	KCS45 16-240											39	16	17	146,30
	20	21	KCS45 20-240											39	19	20	148,60
300	12	13	KCS45 12-300	3	24,5	45	44	13	14	234,30	10	30					
	16	17	KCS45 16-300											45	16	17	238,90
400	12	13	KCS45 12-400	3,5	27	49	44	24	24	338,70	10	34	GU625				
	20	21	KCS45 20-400											49	24	24	334,10

Production on request. Terminals of dimensions other than in chart.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Terminals](#) category:

Click to view products by [Erko](#) manufacturer:

Other Similar products are found below :

[00-054007-01074-6](#) [00-054007-70206-1](#) [00-054007-70210-8](#) [00-054007-70217-7](#) [00-054007-70228-3](#) [00-054007-70256-6](#) [00-054007-70316-7](#) [00-054007-49560-4](#) [00-054007-70209-2](#) [00-054007-70231-3](#) [00-054007-70241-2](#) [00-054007-70242-9](#) [00-054007-70246-7](#) [00-054007-70263-4](#) [00-054007-70288-7](#) [00-054007-70290-0](#) [00-054007-70300-6](#) [00-054007-70304-4](#) [01-2900-1-04412](#) [00581P0075](#) [600TS-10](#) [605601-1](#) [60617-1-C](#) [61314-6-C](#) [61810-3](#) [62149-1](#) [626-0194](#) [63-S](#) [M55155/079C01](#) [M55155/099B03](#) [M55155/109H01](#) [M55155/29XJ08](#) [M55155/30-6S](#) [M55155/30-9S](#) [M55155/30XI09](#) [M6-14RSX](#) [696683-1](#) [696861-1](#) [696999-1](#) [M86700006](#) [D18-110B-C](#) [D18-110B-M](#) [701-1936](#) [701-1955](#) [701-2003](#) [701-2007](#) [701-2013](#) [701-2018](#) [701-2069](#) [701-2077-60](#)