



TYPICAL MOUNTING HOLES
 PANEL THICKNESS: .047-.085 (1.2-2.2)

NOTES:

- MAT'L: NYLON 6/6 (RMS-48).
 FLAME RETARDANT, NYLON 6/6
 UL 94 V-0 (RMS-66),
 AVAILABLE BY SPECIAL ORDER ONLY.
- COLOR: NATURAL.

PART NO.	"L" ±.030 (±0.8)	"A" ±.024 (±0.6)	"B" ±.016 (±0.4)
RN-250-2	2.5 (63.5)	2.0 (50.8)	-
RN-300-2	3.0 (76.2)	2.5 (63.5)	-
RN-350-2	3.5 (88.9)	3.0 (76.2)	-
RN-400-2	4.0 (101.6)	3.5 (88.9)	-
RN-450-2	4.5 (114.3)	4.0 (101.6)	-
RN-500-2	5.0 (127.0)	4.5 (114.3)	-
RN-550-2	5.5 (139.7)	5.0 (127.0)	-
RN-600-2	6.0 (152.4)	5.5 (139.7)	-
RN-650-2	6.5 (164.1)	6.0 (152.4)	-
RN-700-3	7.0 (177.8)	6.5 (164.1)	3.25 (82.2)
RN-750-3	7.5 (190.5)	7.0 (177.8)	3.5 (88.5)
RN-800-3	8.0 (203.2)	7.5 (190.5)	3.75 (94.9)
RN-850-3	8.5 (215.5)	8.0 (203.2)	4.0 (101.6)

G	SEE CO 200086 FOR CHANGES	SK 12.07.07	TITLE: NARROW CARD GUIDE (RN)			DWG IN IN(mm)	FINAL	PRINT TYPE
F	SEE CO 200041 FOR CHANGES	SK 09.28/07						
E	SEE ECN #863 FOR CHANGES	SM 10.04.04	TOLERANCES UNLESS NOTED	FILE # RN	DWN: J.B.	APP:	PART # SEE CHART	CA
D	SEE ECN #831 FOR CHANGES	SM 08.09.04	.XX=±.010	MAT'L: SEE NOTES	DT: 04-08-97	DT:		
C	SEE ECN #547 FOR CHANGES	SM 12.20.02	.XXX=±.005	RE: RICHCO, INC.	RICHCO INC.			
B	SEE ECN #526 FOR CHANGES	SM 11.21.02	FRAC=±1/64	PO BOX 804238, CHICAGO, 60680		(773) 539-4060		
A	ADDED FLAME RET. TO NOTES; CHANGED FILE NO.	SM 02.21.02	ANG=±1°					
REV	DESCRIPTION	ENGR DATE						

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Racks & Rack Cabinet Accessories](#) category:

Click to view products by [ESSENTRA](#) manufacturer:

Other Similar products are found below :

[M00-PLN](#) [F2424](#) [8351-832-A-24](#) [9104](#) [9105](#) [PLFF2000](#) [H-9163-B](#) [1427C3](#) [HTS10](#) [PC-79](#) [SC10-3A](#) [SC4-28](#) [CG3-340S/12](#) [CP-001BK](#)
[M6123-4007-SS](#) [AX61400TB](#) [TS170](#) [LP40](#) [5261304-07](#) [CG3-160G](#) [7112C-PLN](#) [ALUM](#) [CM10](#) [8610-3124-S-26](#) [TS81](#) [7142](#) [GP134](#)
[M6125-4007-A-24](#) [M6127-4007-SS](#) [PBCOVER](#) [512](#) [AEG-4000G](#) [AEG-3000G](#) [HD99](#) [SR2-66A2](#) [FP10B4HP-1](#) [SR16-66A2](#) [FP52-2](#) [1406-](#)
[1006-01](#) [29478](#) [TS2535](#) [TS169-6](#) [CAC2](#) [HA19-3U](#) [BR-19-10-1](#) [TS180](#) [CG3-ESD](#) [SC11-1](#) [CFS-1.00/2.20](#) [HEC0800PB](#) [ZC633R](#)