

# 80A Mini AC/DC Clamp Meter

## Small diameter elongated jaw

Designed for high resolution current measurements in hard to reach locations. This mini-clamp performs AC and DC low current tests where typical clamps cannot go.

### Features:

- 4000 count LCD display
- 4A range with 1mA resolution for accurate low current measurements
- Jaw opens to 0.5" (12.7mm)
- AC/DC Voltage, Resistance, Frequency, Capacitance, and Duty Cycle
- Diode Test/Continuity Beeper
- Data Hold
- Complete with test leads, two 1.5V AAA batteries, and carrying case



Mini size jaw conveniently reaches into narrow spaces for taking Current measurements where typical clamp size meters cannot go.



Specifications	Range	Resolution	Accuracy (%rdg+digits)
AC Current	4A, 80A	1mA	±(2.5% + 5d)
DC Current	4A, 80A	1mA	±(2.5% + 4d)
AC Voltage	400mV to 600V	0.1mV	±(2.0% + 4d)
DC Voltage	400mV to 600V	0.1mV	±(1.5% + 3d)
Resistance	400Ω to 40MΩ	0.1Ω	±(1.5% + 2d)
Frequency	5Hz to 10MHz	0.001Hz	±(1.2% + 3d)
Duty Cycle	5 to 99.9%	0.1%	±(1.2% + 3d)
Dimension/Weight	8.3x2.8x1.5" (210x70x37mm)/7oz (200g)		

### Ordering Information:

380950 .....80A Mini AC/DC Clamp Meter



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Clamp Multimeters & Accessories](#) category:*

*Click to view products by [Extech](#) manufacturer:*

Other Similar products are found below :

[I800](#) [FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [UT233](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#)  
[BM162](#) [BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE I200](#) [FLUKE I200S](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)  
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)  
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)  
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 4000A 350MM](#)