

MA430 Series 400A Clamp Meters + NCV



Compact size allows measurements in tight locations and Built-in non-contact Voltage detector with LED alert. Three models to choose from with True RMS option and advanced multimeter functions.



Features

- Built-in non-contact Voltage detector with LED alert
- Backlit LCD display
- 1.2" (30mm) jaw size for conductors up to 350MCM
- True RMS models for MA430T/MA435T and multimeter functions included on all clamp meters
- CAT III - 600V rating
- Data Hold
- Low battery indication and Auto Power Off
- Complete with test leads, general purpose Type K bead wire temperature probe (for MA435T), 9V battery, and soft case

Specifications	MA430 / MA430T	MA435T	Basic Accuracy
Display counts	2000	4000	
True RMS	— / Yes	Yes	
AC Current (max res.)	400A (0.001A)	400A (0.01A)	±(2.5% + 8d)
DC Current (max res.)	—	400A (0.01A)	±(2.5% + 5d)
AC Voltage (max res.)	600V (0.1mV)	600V (0.1mV)	±(1.5% + 5d)
DC Voltage (max res.)	600V (0.1mV)	600V (0.1mV)	±(1.5% + 2d)
Resistance (max res.)	20MΩ (0.1Ω)	40MΩ (0.1Ω)	±(1.5% + 2d)
Frequency (max res.)	—	10Hz to 10kHz	±(1.5% + 2d)
Capacitance (max res.)	—	100μF (0.01nF)	±(3.0% + 5d)
Temperature (max res.)	—	-4 to 1400°F/-20 to 760°C (0.1°)	±(3% + 9°F/5°C)
Diode/ Continuity	Yes	Yes	
Dimensions/ Weight	7.8x2.8x1.6" (197x70x40mm)/ 6.5oz (183g)		

Ordering

- MA430 400A AC Clamp Meter + NCV
 MA430T 400A True RMS AC Clamp Meter + NCV
 MA435T 400A True RMS AC/DC Clamp Meter + NCV



X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Clamp Multimeters & Accessories](#) category:

Click to view products by [Extech](#) manufacturer:

Other Similar products are found below :

[FLUKE 1630-2](#) [ZAPDUMOD-03](#) [ZARKMS-01-99](#) [TESTO 770-3](#) [0590 7703](#) [AX-3550](#) [AX-M266C](#) [BM079](#) [BM089](#) [BM157](#) [BM162](#)
[BM197](#) [KEW2210R](#) [FLUKE 80I-110S](#) [FLUKE A3002FC](#) [FLUKE I200](#) [FLUKE I3000FLEX-24](#) [FLUKE I310S](#) [FLUKE I400](#) [CIE600](#)
[TESTO 770-2](#) [0590 7702](#) [34194A](#) [KEW2433R](#) [KEW8112](#) [FLUKE 772](#) [380976-K](#) [MA3110](#) [MA440](#) [MA443](#) [MA445](#) [FLUKE-374 FC](#)
[TA74](#) [AMP-320](#) [CM55](#) [CM46](#) [I200](#) [ACD-6 PRO](#) [FLUKE-1630-2FC](#) [I410](#) [CM44](#) [CM42](#) [FLK-A3000 FC](#) [FLUKE-376 FC](#) [ACD-14-PRO](#)
[MA610](#) [F201](#) [F205](#) [MA193 \(250 MM\)](#) [DIGIFLEX 400A 170MM](#) [DIGIFLEX 400A 250MM](#) [PAC 93](#)