


SPECIFICATION FOR APPROVAL

| | | | | |
|-----------|--------------|-------|----------|--------------|
| COMMODITY | PK CHOKE | | SPEC NO. | SP-090526007 |
| ITEM | COIL1016-3.3 | Green | D | QRRD-01-02 |

| (1) DIMENSION: (UNIT: mm) | | DIM. | TOL. |
|--|---|------|------|
|  <p>UL TUBE</p> | A | 11.5 | MAX. |
| | B | 17.5 | MAX. |
| | C | 16.0 | ±3.0 |
| | D | 0.8 | ±0.1 |
| | E | 6.0 | ±0.5 |
| | F | 3.0 | MAX. |
| | G | | |
| | H | | |
| | I | | |
| | J | | |

| (2) ELECTRICAL CHARACTERISTIC | TEST INSTRUMENTS. | | |
|-------------------------------|-------------------|-----|---|
| INDUCTANCE | 3.3 ± 10% | mH | <input checked="" type="checkbox"/> AGILENT 4294A Precision Impedance Analyzer. <input type="checkbox"/> AGILENT 4285A Precision L.C.R. Meter. <input type="checkbox"/> HP-4286A RF L.C.R. Meter. |
| TEST FREQUENCY | 1 | kHz | <input type="checkbox"/> ZENITECH 3302 Automatic Components Analyzer. <input type="checkbox"/> ZENITECH 101 L.C.R. Meter. |
| TEST VOLT | 0.25 | V | <input type="checkbox"/> WAYNE KERR 6420 Precision Impedance Analyzer. <input checked="" type="checkbox"/> ZENITECH 1320 BIAS CURRENT. <input checked="" type="checkbox"/> ZENITECH 502AC Resistance Meter. |
| RDC | 3.12 (max) | Ω | <input type="checkbox"/> ADEX AX-1155B DC Low Ohm Meter. |
| Isat | 0.32 (max) | A | |
| Irms | 0.75 (max) | A | |

REMARK :

1. Inductance drop = 10% typ at Isat.
2. ΔT = 40°C rise typ at Irms.

SPECIFICATION FOR APPROVAL

| COMMODITY | PK CHOKE | | SPEC NO. | SP-090526007 |
|--------------------------|--------------|----------------------------------|-------------|--------------|
| ITEM | COIL1016-3.3 | Green | D | QRRD-01-02 |
| (3) Material List | | | | |
| NO | ITEM | MATERIAL | NOTE | |
| 1 | CORE | DR2W 10*16 Or other's equivalent | | |
| 2 | WIRE | UEW Or other's equivalent | 130°C CLASS | |
| 3 | SOLDER | 100H Or other's equivalent | | |
| 4 | TUBE | Heat Shrinkable tube | | |
| | | | | |
| | | | | |
| | | | | |
| | | | | |
| | | | | |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Fixed Inductors](#) category:

Click to view products by [Ferrocore](#) manufacturer:

Other Similar products are found below :

[MLZ1608M6R8WTD25](#) [MLZ1608N6R8LT000](#) [MLZ1608N3R3LTD25](#) [MLZ1608N3R3LT000](#) [MLZ1608N150LT000](#)
[MLZ1608M150WTD25](#) [MLZ1608M3R3WTD25](#) [MLZ1608M3R3WT000](#) [MLZ1608M150WT000](#) [MLZ1608A1R5WT000](#)
[MLZ1608N1R5LT000](#) [B82432C1333K000](#) [PCMB053T-1R0MS](#) [PCMB053T-1R5MS](#) [PCMB104T-1R5MS](#) [CR32NP-100KC](#) [CR32NP-151KC](#) [CR32NP-180KC](#) [CR32NP-181KC](#) [CR32NP-1R5MC](#) [CR32NP-390KC](#) [CR32NP-3R9MC](#) [CR32NP-680KC](#) [CR32NP-820KC](#)
[CR32NP-8R2MC](#) [CR43NP-390KC](#) [CR43NP-560KC](#) [CR43NP-680KC](#) [CR54NP-181KC](#) [CR54NP-470LC](#) [CR54NP-820KC](#) [CR54NP-8R5MC](#)
[MGDQ4-00004-P](#) [MGDU1-00016-P](#) [MHL1ECTTP18NJ](#) [MHL1JCTTD12NJ](#) [PE-51506NL](#) [PE-53601NL](#) [PE-53630NL](#) [PE-53824SNLT](#) [PE-62892NL](#) [PE-92100NL](#) [PG0434.801NLT](#) [PG0936.113NLT](#) [PM06-2N7](#) [PM06-39NJ](#) [HC2LP-R47-R](#) [HC2-R47-R](#) [HC3-2R2-R](#) [HC8-1R2-R](#)