

Thermocouple with cable and lug

Series 71-KFT

71-KFT is a series of thermocouple probes with a metal protection tube and thermocouple cable with free ends or terminated by electrical connector according to individual arrangements (socket, plug).

The metal cover protects the measuring hot-junction from direct contact with the medium and enables proper positioning and installation of the probe.



Description


| | |
|----------------|------------------------|
| Type | 71-39010001-0300.M4.TM |
| Article number | 16019825 |

Thermocouple 1x Fe-CuNi/J with fiberglass insulated cable with external metal braid. Thermocouple hot-junction is grounded to the cable lug. The wires of the cable are colored in accordance with the IEC 60584 standard.

Technical parameters

| | |
|---------------------------|---------------------------|
| Thermocouple | 1x Fe-CuNi/J |
| Thermocouple hot junction | grounded |
| Measuring range | 0...+400°C |
| Accuracy | class 1 acc. to IEC 60584 |
| Mounting hole ID | for screw M4 |
| Dimension, width B | 8mm |
| Cable lug material | tinned copper |
| Cable length AL | 3000mm |
| Cable insulation | fiberglass / metal braid |
| Cable ambient temperature | 0...+ 400°C |
| Cable termination | free ends 50mm |

Marking

| | |
|------------------------------------|---|
| Wire markings acc. to IEC 60584 |  |
|------------------------------------|---|

Mounting accessories, screw fittings, flanges, mounting connectors, plugs and sockets are included in other catalog cards and on the website.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Board Mount Temperature Sensors](#) category:

Click to view products by [Guenther](#) manufacturer:

Other Similar products are found below :

[5962-8757102XA](#) [66F115](#) [MCP9808-EMS](#) [MCP98242T-BEMNY](#) [MCP9843T-BEMC](#) [EMC1063-1-ACZL-TR](#) [NCT218FCT2G](#)
[O53GAB175A-160Y](#) [OH10/62,112](#) [3610085020002](#) [389049M9527](#) [TC622EAT](#) [TC6501P095VCTTR](#) [TC6501P105VCTTR](#)
[TC6501P125VCTTR](#) [MCP9802A0T-M/OT](#) [MCP9803T-M/SN](#) [MCP9843-BEST](#) [TC6501P115VCTTR](#) [TC6502P065VCTTR](#)
[ADM1023ARQZ-REEL](#) [ADM1024ARUZ-REEL](#) [ADM1032ARMZ-1RL](#) [AT30TS74-U1FMBB-T](#) [AT30TS74-U1FMAB-T](#) [AT30TS74-](#)
[U1FMCB-T](#) [AT30TS74-U1FMDB-T](#) [ADT7483AARQZ-RL](#) [ADT7481ARMZ-REEL](#) [ADT7463ARQZ-REEL](#) [MCP98243T-BEMNY](#)
[MCP98243T-BE/MC](#) [66L080-0226](#) [MAX31820MCR+T](#) [MAX1452CAEC8H](#) [DS1780E](#) [TMP05BKSZ-REEL7](#) [5962-8757103XA](#) [WTK-14-](#)
[36/N](#) [E52-CA6D-N 4M](#) [MCP98244T-BEMNY](#) [MCP9802A5T-MOT](#) [MAX6581TG9A+T](#) [DS75S-C11+T&R](#) [S-58LM20A-I4T1U](#)
[MAX6501UKP120+T](#) [MCP98243T-BE/ST](#) [AT30TS01-MAA5M-T](#) [NCT375DR2G](#) [DS18S20-SL+T&R](#)