

NEW FM2032 – Micro Soldering Iron kit

The Hakko FM2032-52 Micro Soldering Iron kit consist of a slender, light-weight hand piece that extends precision micro soldering capabilities to a variety of Hakko soldering and rework systems.

The FM-2032 ESD-safe soldering iron uses the quick change T30 Series composite micro soldering tips engineered for optimal heat transfer and the ability to reach into tight areas.



Features

- Connects to FX951, FM203 & FM206 stations
- Compatible with T30 series micro tips
- Temperature range 200° - 450°C
- Light weight handle with cool running grip
- Burn resistant cord
- ESD safe

Included with the FM2032-52 Micro Soldering Iron Conversion Kit:

- 1 - FM2032-51 Hand piece only
- 1 - B3253 Connecting cable
- 1 - FH200-81 Iron holder
- 1 - B2300 Heat resistant pad

Note: No tips supplied with kit

NEW FM2032 – Micro Soldering Iron kit

Specification

Model Name	FM2032
Part Number- Kit	FM2032-52
Power Consumption	48W
Tip-to-Ground Potential	< 2mV
Tip-to-Ground Resistance	< 2 ohms
Total Length with tip, w/o cord	170 mm
Length of cord	1.2 m

Optional tips

P/N	Description
T30-D06	Soldering tip shape 0.6D
T30-D1	Soldering tip shape 1D
T30-I	Soldering tip shape I
T30-J	Soldering tip shape J
T30-KU	Soldering tip shape KU
T30-KN	Soldering tip shape KN

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [hakko manufacturer](#):

Other Similar products are found below :

[A1006](#) [FT8002-01](#) [PTG-2T1G0008](#) [HFJ11-1G06ERL](#) [HFJ12-E2450ER-L11RL](#) [TG110-RP55N5LF](#) [B3048](#) [T30-D06](#) [T12-D12](#) [FM203-15](#)
[A1014](#) [T12-D24](#) [611-2](#) [FM2023-04](#) [FT8003](#) [G3-1601](#) [T31-01JS02](#) [T33-BC4](#) [T33-BC5](#) [T33-D24](#) [N50B-05](#) [N50B-06](#) [950-CK](#) [A1013](#)
[A1067](#) [A1187B](#) [A1379](#) [B1309](#) [B1787](#) [C1392B](#) [A1553](#) [A1554](#) [FX300-03](#) [FT300](#) [918-T-1.6D/P](#) [C1148B/P](#) [111-SA](#) [B5045](#) [B5046](#) [N60-09](#)
[T12-1612](#) [C1148B](#) [HFJ11-1G11E-L11RL](#) [TG41-2006NRLTR](#) [T30-KU](#) [T12-BC2](#) [N51-01](#) [T30-D1](#) [T18-CF1](#) [A1503](#)