

PART NO. : TD01-0406NERL

6PIN DIP TRANSFORMER

DESIGNED FOR USE IN T3,DS3,E3
AND STS-1 INTERFACES

RETURN LOSS MEETS G.703 REQUIREMENTS

LEAD-FREE/RoHS COMPLIANT

COMPATIBLE TO LEAD-FREE WAVE SOLDERING
PROCESS FOR THROUGH HOLE COMPONENTS

OPERATING TEMPERATURE 0-70°C

ELECTRICAL SPECIFICATIONS @25° C

URNS RATIO

P1-3:P6-4 1:1±2%

OCL P1-P3

40µH min

LL P1-3

0.1µH max


BANDWIDTH (75Ω)

0.200-340MHz typ

ISOLATION

1,500Vrms

DIMENSIONS: Inch [mm]
TOLERANCES: ±0.005 IF NOT SPECIFIED



HALO/PBL

CALIFORNIA, USA
KOWLOON, HONG KONG
SINGAPORE

TITLE	6PIN DIP TRANSFORMER		SIGNATURES	DATE	REV.	DESC.	DATE
	FOR	T3/DS3/E3/STS-1					
PART NO.	TD01-0406NERL		CHECKED				
SCALE	NONE	PAGE	1 OF 1	APPROVED			
				FILE	TD01NERL.DWG		

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Audio Transformers](#) / [Signal Transformers](#) category:

Click to view products by [Hakko](#) manufacturer:

Other Similar products are found below :

[CX2041NLT](#) [MGPWT-00449-P](#) [PE-64961](#) [H1302FNLT](#) [H5008FNL](#) [H5012FNL](#) [H5020FNLT](#) [H5077NLT](#) [H5079NLT](#) [H5084FNLT](#)
[B78476A9558A003](#) [1812WBT2-4](#) [1879479-1](#) [HX2260FNL](#) [HX5014FNL](#) [EX2024FNL](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [PE-65848FNLT](#) [H1174FNL](#) [H1302FNL](#) [H5015FNL](#) [H5019EFNL](#) [H5062FNLT](#) [CX2047LNL](#) [MGPWT-00059-P](#) [MGPWT-00266-P](#) [MGPWT-00278-P](#) [MGPWT-00431-P](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [BX1194WNLT](#) [HX1234NLT](#) [HX5008FNLT](#) [HX5019FNL](#) [HX5084NL](#) [3-1879385-5](#) [TX1263NLT](#) [4-1879391-0](#) [T1142NL](#) [HX6101FNL](#) [HX5084FNL](#) [HX1148NL](#) [HX5020FNLT](#) [HX5014FNLT](#) [T1124NL](#)
[1879732-1](#)