


10GBASE-T Transformer

SMD 10GBASE-T 24-Pin Single Port Isolation Modules



Product Features:

- 10GBASE-T Ethernet Transformer/CMR Choke
- IEEE802.3an/af/at/bt Compliant Options
- 4PPoE - 4 Pair Power over Ethernet Available
- UL/EN60950 Recognized
- 100% Electrical Testing
- 1500Vrms Hi-Pot
- Patented Open Frame Construction

Part Number	Data Rate	Circuit	Total Power ¹	Current Per Pair	Operating Temp	Package	Max Height inch [mm]
TG10G-S100NJLF	10G	A	-	-	0 to 70°C	NJ	0.250 [6.35]
TG10G-S101NJLF	10G	B	-	-	0 to 70°C	NJ	0.250 [6.35]
TG10G-S102NJLF	10G	C	-	-	0 to 70°C	NJ	0.250 [6.35]
TG10G-RP02NJLF ³	10G	C	30W	350mA	0 to 70°C	NJ	0.250 [6.35]
TG10G-S12NZ5LF	10G	C	30W	350mA	0 to 70°C	NZ5	0.255 [6.48]
TG10G-E12NZ5LF	10G	C	30W	350mA	-40 to +85°C	NZ5	0.255 [6.48]
TG10G-HP6NZ5LF	10G	C	60W	600mA	0 to 70°C	NZ5	0.255 [6.48]
TG10G-HPE6NZ5LF	10G	C	60W	600mA	-40 to +85°C	NZ5	0.255 [6.48]
TG10G-HP10NZ5LF	10G	C	90W	1A	0 to 70°C	NZ5	0.255 [6.48]
TG10G-HPE10NZ5LF	10G	C	90W	1A	-40 to +85°C	NZ5	0.255 [6.48]

Notes:

¹ Power rating reduced to half when using only two pairs for power as in 802.3af/802.3at applications.


² The IEEE802.3bt standard has not been officially ratified.

³ Can be used in -40 to +85°C for non-PoE applications.


· Please contact the factory or representative for individual datasheets or additional information.

· Footprint interchangeable 2.5G/5G parts available at: <https://www.haloelectronics.com/pdf/discrete-single-2G5G.pdf>


Circuit A



Circuit B



Circuit C



For additional information contact your [local representative](#), or HALO's support staff at (650) 903-3800 or info@haloelectronics.com

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Audio Transformers](#) / [Signal Transformers](#) category:

Click to view products by [HALO](#) manufacturer:

Other Similar products are found below :

[749023020](#) [CU4S0506AT-2655-H1](#) [MET-58](#) [PE-64961](#) [H5008FNL](#) [H5020FNLT](#) [H5079NLT](#) [1879479-1](#) [1879564-1](#) [PA1277NLT](#)
[PA1528ANL](#) [PA2007NLT](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [HX1234NLT](#) [HX5008FNLT](#)
[100B-1001XNL](#) [PA1282NLT](#) [HX5084FNL](#) [T1108NLT](#) [2-1879391-5](#) [TTC-266-2](#) [3-1879385-4](#) [PA1032NL](#) [H2009FNLT](#) [PA0801NLT](#)
[TTC-266](#) [X-1619](#) [SM51295PEL](#) [T5008NLT](#) [PE-68517T](#) [HX1294NLT](#) [HX5084FNLT](#) [H5015FNLT](#) [H6080NLT](#) [CX2024NL](#) [HX1294FNLT](#)
[TX1473NLT](#) [PE-69011NLT](#) [CX2047LNLT](#) [CX2043LNLT](#) [DCT20EFD-U32S003](#) [H5120NLT](#) [H7137FNLT](#) [H1259NLT](#)