



Quality Products. Service Excellence.

# Miniature Audio Epoxy Potted 106 Series

PC Board Mount

## Features



- Output power models from 5 to 1,500 milliwatt level available.
- P.C. board mount - square pin type (0.025" square typical) - see mechanical information below for lengths.
- Bifilar winding technique used on center tapped units for balanced resistive and capacitive characteristics.
- Rugged black epoxy potted construction produces a completely sealed unit withstanding severe environmental conditions including those of MIL-T-27 (Grade 5, Class S).
- For the more economical open type P.C. mount types please refer to the **148** and **149** series.
- Peak working voltage rating of: 200V
- Referring to figures 1-9, if connection is not used - no pin will exist.



## Gallery



Part No.	Typical Application	Nominal Impedance (Ohms)		Max. Primary D.C. ma. (*1)	D.C. Resistance (Ohms) +/- 15%		Output Milliwatts (*2)	Insertion Loss db (*3)	Low Frequency Roll Off -1 db (Hz.) (*4)	Drawing Figure
		Primary	Secondary		Primary	Secondary				
106C	Input	50000	1,500 ct	0	2400	52	10	1	60	7
106E	Input	600 ct	600	9	65	83	500	1	150	8
106EE	Input	600 ct	600 ct	9	65	83	500	1	150	9
106G	Interstage	4000	600 ct	10	340	24	150	1	215	7
106H	Interstage	4000	2,600 ct	10	340	100	150	1	215	7
106J	Interstage	10000	2,000 ct	6.5	700	89	150	1	215	7
106M	Interstage	20000	2,000 ct	4.5	1180	89	150	1	215	7
106Q	Output	48 ct	3.2	32	2.4	0.3	1500	1	170	8
106R	Output	48 ct	8	32	2.4	0.7	1500	1	170	8
106S	Output	100 ct	3.2	22	4.4	0.3	1500	1	170	8
106T	Output	100 ct	8	22	4.4	0.7	1500	1	170	8
106V	Output	250 ct	8	14	11	0.7	1500	1	170	8
106W	Output	500 ct	3.2	10	26	0.3	1500	1	170	8
106X	Output	500 ct	8	10	26	0.7	1500	1	170	8

Data subject to change without notice

© 2022. Hammond Manufacturing Ltd. All rights reserved.



## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Audio Transformers](#) / [Signal Transformers](#) category:*

*Click to view products by [Hammond](#) manufacturer:*

Other Similar products are found below :

[CX2041NLT](#) [MGPWT-00449-P](#) [PE-64961](#) [H1302FNLT](#) [H5008FNL](#) [H5012FNL](#) [H5020FNLT](#) [H5077NLT](#) [H5084FNLT](#)

[B78476A9558A003](#) [1812WBT2-4](#) [1879479-1](#) [HX2260FNL](#) [HX5014FNL](#) [EX2024FNL](#) [FL1066](#) [T1137NLT](#) [T3012NL](#) [PE-65812FNL](#) [PE-](#)

[65848FNLT](#) [H1174FNL](#) [H1302FNL](#) [H5015FNL](#) [H5019EFNL](#) [H5062FNLT](#) [CX2047LNL](#) [MGPWT-00059-P](#) [MGPWT-00266-P](#) [MGPWT-](#)

[00278-P](#) [MGPWT-00431-P](#) [TTC-100](#) [TTC-143-H](#) [TTC-5032-1](#) [BX1194WNLT](#) [HX1234NLT](#) [HX5008FNLT](#) [HX5019FNL](#) [HX5084NL](#) [3-](#)

[1879385-5](#) [TX1263NLT](#) [4-1879391-0](#) [P2004NLT](#) [T1142NL](#) [HX6101FNL](#) [HX5084FNL](#) [HX1148NL](#) [HX5020FNLT](#) [HX5014FNLT](#)

[T1124NL](#) [1879732-1](#)