



适应基板厚度: 1.2mm~1.6mm
 温度范围: -25°C~85°C
 额定电压: 250V AC/DC
 额定电流: 1A
 绝缘电阻: ≥1000MΩ
 耐压: 800V AC/minute

| | | | |
|-----|-------|-------|-------|
| 15 | 23 | 21.00 | 24.00 |
| 14 | 21.5 | 19.50 | 22.50 |
| 13 | 20 | 18.00 | 21.00 |
| 12 | 18.5 | 16.50 | 19.50 |
| 11 | 17 | 15.00 | 18.00 |
| 10 | 15.5 | 13.50 | 16.50 |
| 9 | 14 | 12.00 | 15.00 |
| 8 | 12.5 | 10.50 | 13.50 |
| 7 | 11 | 9.00 | 12.00 |
| 6 | 9.5 | 7.50 | 10.50 |
| 5 | 8 | 6.00 | 9.00 |
| 4 | 7.5 | 4.50 | 7.50 |
| 3 | 6 | 3.00 | 6.00 |
| 2 | 4.5 | 1.50 | 4.50 |
| Pin | DIM.A | DIM.B | DIM.C |

| | | | |
|-----------|--------------|----------------|-------------------|
| 1502H-XXP | PA66 UL94V-0 | 1502W | 1502T |
| PART NO | Material | Suitable Wafer | Suitable Terminal |

| | | | | | | | | | |
|----------|---------|--------------|----------------|------------------------|---------------------------------------|------------|----------|------------|-------|
| — | | new | | 2015/5/3 | | A | | 瀚源 | |
| ECN BO. | | DESCRIPTION. | | DATE. | | REV. | | | |
| DESIGNED | CHECKED | APPROVAL | DRAWING NUMBER | | | SCALT: 1/2 | | SCALE: 3:1 | |
| Mikey | Tom | Jerry | PART NAME | 1502H-XXP | UNLESS OTHERWISE SPECIFIED,TOLERANCE: | | X. | ±0.25 | |
| | | | MODEL NAME | H-1502H-XXP | | | X.x | ±0.20 | |
| | | | 3RD ANGLE PROJ | HanElectricity Co.,LTD | | | | X.xx | ±0.15 |
| | | | | | | | FILE.NO. | | |

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [HanElectricity](#) manufacturer:

Other Similar products are found below :

[0015917161](#) [0022155065](#) [57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [71.350.2428.0](#) [733-134](#) [733-162](#) [760-3052](#) [MHR-64-VUAL](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [801-43-002-10-013000](#)
[801-43-006-10-002000](#) [803-43-024-10-001000](#) [803-93-012-10-001000](#) [8-1437020-4](#) [819-22-004-30-001101](#) [820-22-006-30-001101](#)
[820-22-008-30-001101](#) [821-22-002-10-001101](#)