



	Crimping inner conductor	Crimping outer conductor
Hand tool	09 99 000 0501	09 99 000 0503
Locator	09 99 000 0507	09 99 000 0508
Cables	RG174U, RG188AU, RG316U	
Cavity		B
Tool setting	Conductor cross-section	Selection
	AWG 24	SEL 5
	AWG 26	SEL 5
	AWG 28	SEL 4
	AWG 30	SEL 3

0969 282 7140	Mating area	0,2 μm Au	0,2 μm Au
	Termination area	5 μm Sn	0,2 μm Au
0969 282 5140	Mating area	0,8 μm Au	1,3 μm Au
	Termination area	0,2 μm Au	1,3 μm Au
Part number	Plating	outer conductor	inner conductor

	All rights reserved	Scale 5:1	Free size tol.	Ref.
	Department EC PD - CN	Created by ZHUANGJ	Inspected by LUOK	Standardisation HOFFMANN
HARTING Electronics GmbH D-32339 Espelkamp		Title male coaxial contact 50 Ohm straight cable termination		Date 2017-01-25
		Type TB	Number 0969282X140	State Final Release
				Doc-Key / ECM-Nr. 100706793/UGD/000/A 500000114200
				Rev. A Page 1/1

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [D-Sub Contacts](#) category:

Click to view products by [HARTING](#) manufacturer:

Other Similar products are found below :

[D02-22-26S-10000](#) [8656352067LF](#) [131A15029X](#) [132J22039X](#) [132A11029X](#) [132A11049X](#) [132A12059X](#) [1757912-1](#) [188582-000](#)
[162A11889X](#) [1757913-1](#) [212558-1](#) [030-1955-000](#) [053744-0098](#) [053744-0099](#) [053745-0105](#) [053745-0111](#) [601098N003](#) [D-610-10CS2962](#)
[86303057NLF](#) [131A11019X](#) [162A11819X](#) [40-9854MP](#) [1-208778-5](#) [FC120N2](#) [MC7526D/AA](#) [MC8122D/AA](#) [FC4010D-15](#) [FC4006D](#)
[121A05329A](#) [164C16669X](#) [86566620064LF](#) [131A13019X](#) [DLS3XS5AK40X](#) [09692825723](#) [030-1954-000](#) [L17DM53744207](#)
[L17RRD1M11400](#) [030-1952-000](#) [030-1953-000](#) [030-1953-030](#) [132C11039X](#) [132J15019X](#) [132C15019X](#) [131A10029X](#) [8638PSC2006LF](#)
[8656453067LF](#) [86566520064LF](#) [L17DM537441](#) [L17DM537425001](#)