



HelaGuard Accessories


- ALPA PA66 Locknuts

The ALPA hexagonal locknut is used to secure fitting.



HelaGuard ALPA PA66 Locknuts.

MATERIAL	Polyamide 6.6, glass-fibre reinforced (PA66GF30%)
Operating Temperature	-50 °C to +135 °C



HelaGuard locknut



TYPE	Thread Size	A/F Nut (A/F3)	Outside Ø max (OD max.)	Thickness (T)	Pack Cont.	Colour	Article-No.
ALPA-M12	M12	18	20	5	10 pcs.	Black (BK)	166-50133
ALPA-M16	M16	22	24	5	10 pcs.	Black (BK)	166-50134
ALPA-M20	M20	26	29	6	10 pcs.	Black (BK)	166-50135
ALPA-M25	M25	32	35	6	10 pcs.	Black (BK)	166-50136
ALPA-M32	M32	41	46	7	2 pcs.	Black (BK)	166-50137
ALPA-M40	M40	50	55	7	1 pcs.	Black (BK)	166-50138
ALPA-M50	M50	60	66	8	1 pcs.	Black (BK)	166-50139
ALPA-M63	M63	75	83	8	1 pcs.	Black (BK)	166-50140
ALPA-PG7	PG7	19	21	5	10 pcs.	Black (BK)	166-50141
ALPA-PG9	PG9	22	24	5	10 pcs.	Black (BK)	166-50142
ALPA-PG11	PG11	24	26	5	10 pcs.	Black (BK)	166-50143
ALPA-PG13	PG13.5	27	29	6	10 pcs.	Black (BK)	166-50144
ALPA-PG16	PG16	30	33	6	10 pcs.	Black (BK)	166-50145
ALPA-PG21	PG21	36	39	7	10 pcs.	Black (BK)	166-50146
ALPA-PG29	PG29	46	50	7	1 pcs.	Black (BK)	166-50147
ALPA-PG36	PG36	60	66	8	1 pcs.	Black (BK)	166-50148
ALPA-PG42	PG42	65	73	8	1 pcs.	Black (BK)	166-50149
ALPA-PG48	PG48	70	78	8	1 pcs.	Black (BK)	166-50150

All dimensions in mm. Subject to technical changes.
Minimum Order Quantity (MOQ) may differ from package content.

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Conduit Fittings & Accessories](#) category:

Click to view products by [HellermannTyton](#) manufacturer:

Other Similar products are found below :

[790-3006](#) [790-3150](#) [RE42](#) [LT20090](#) [LTB15045](#) [LTB20045](#) [LTB3890](#) [CGE195](#) [790-3154](#) [790-3008](#) [790-3014](#) [790-3020](#) [790-3152](#) [790-3156](#) [790-3166](#) [790-3002](#) [790-3162](#) [C2016-P](#) [C2012-P](#) [561-87BG11BLK](#) [1.511.1601.50](#) [55502675](#) [2676](#) [302-TB](#) [655241-000](#) [C17](#) [262-420](#) [TMC165-BR](#) [RBDP-BLA-20D236U](#) [RBDP-BLA-30D346U](#) [SPL25/075/M](#) [CN21](#) [SRN21](#) [3405B](#) [4975](#) [VC12516](#) [RC156-0500](#) [DM0523-1/2A](#) [1035A](#) [DMS0250-1A](#) [DMS0313-1A](#) [1040A](#) [1050A](#) [R1/8A](#) [DMPC0490-1/2A](#) [DMPC0521-1/2A](#) [DMPC0552-1/2A](#) [1070A](#) [R1/2A](#) [E1-7/8B](#)