


SEALED WITH  
EPOXY POTTING  
COMPOUND

ANSI Y14.5M-1982 APPLIES

THIS DRAWING COVERS A PROPRIETARY ITEM AND IS THE PROPERTY OF MICRO SWITCH, A DIVISION OF HONEYWELL. THIS DRAWING IS NOT TO BE COPIED OR USED WITHOUT THE APPROVAL OF MICRO SWITCH

THIRD ANGLE PROJECTION



SCALE 2:1

DO NOT SCALE PRINT

UNLESS OTHERWISE SPECIFIED  
TOLERANCES ARE

ONE PLACE	(.0)	±.030
TWO PLACE	(.00)	±.015
THREE PLACE	(.000)	±.005
ANGLES		±

WEIGHT

CHARACTERISTICS	ELECTRICAL DATA
OPERATING FORCE AT ROLLER- - - -16 OZ MAX	CONTACT ARRANGEMENT <b>SPNO-DB</b>  10 AMP 125/250 VAC 7.5 AMP 28 VDC IND
RELEASE FORCE AT PLUNGER- - - - 5 OZ MIN	
PRETRAVEL- - - - - .115 MAX	
DIFFERENTIAL TRAVEL- - - - .058 MAX	
OVERTRAVEL- - - - - .025 MIN	

**NOTES**

1. SWITCH SEALED PER MIL-PRF-8805 SYMBOL 3, WATERTIGHT
2. BASIC SWITCH MIL-PRF-8805/7 TYPE
3. STAINLESS STEEL PLUNGER & ROLLER
4. ENCLOSURE TO MEET REQ. OF U.S. ARMY TANK AUTOMOTIVE COMMAND NO. 7748750
5. ROLLER ARM IS PHOS. BRONZE

CATALOG LISTING  
**PL-100**  
PAGE 1 OF 1

REPLACES  
PR-24202

ISSUE  
**M**  
2

REVISIONS

A	200166	J J A	29 MAR 00
---	--------	-------	-----------

CHECK

10 AUG 99

J A F

CHECK

10 AUG 99

G J W

DRAWN

## X-ON Electronics

Largest Supplier of Electrical and Electronic Components

*Click to view similar products for [Basic / Snap Action Switches](#) category:*

*Click to view products by [Honeywell](#) manufacturer:*

Other Similar products are found below :

[5SM901-S12](#) [5SM9-S12N195](#) [01.098.1358.1](#) [602EN532](#) [602EN535-RB](#) [602HE5-RB1](#) [604HE162](#) [604HE223-6B](#) [624HE17-RB](#) [6HM82](#)  
[6HM89](#) [6SE1](#) [6SX1-H58](#) [70500216](#) [70599106](#) [MBD5B1](#) [MBH2731](#) [73-316-0012](#) [EXD-AR20](#) [79211923](#) [79218589](#) [7AS12](#)  
[MIL30126AB6BBMD4A12XAU](#) [ML-1155](#) [ML-1376](#) [831010C3.0](#) [831090C2.EL](#) [83131904](#) [84212012](#) [8AS239](#) [8HM73-3](#) [8SX26-H33](#)  
[914CE1-6G](#) [PL-100](#) [11SM1077-H4](#) [11SM1077-H58](#) [11SM1-TN107](#) [11SM405](#) [11SM8423-H2](#) [11SX37-T](#) [11SX48-H58](#) [11SM2442-T](#)  
[11SM76-T](#) [11SM77-H58](#) [11SM77-T](#) [11SM863-T](#) [11SM866](#) [A7CN-1M-1-LEFT](#) [A831700C7.0](#) [121EN187-R](#)