


技术参数 SPECIFICATIONS


- ❑ 线数 (Poles) : (YS、YSB)2~25x2 (AS、WAS)2~40x2
- ❑ 适用线规 (Applicable wires) : AWG30#~24#
- ❑ 适应基板厚度 (Applicable PC board thickness) : 1.6mm
- ❑ 温度范围 (Temperature range) : -25℃~85℃
- ❑ 额定电压 (Voltage rating) : 250V.Ac/Dc
- ❑ 额定电流 (Current rating) : 2A
- ❑ 接触电阻 (Contact resistance) : $\leq 0.02\Omega$
- ❑ 绝缘电阻 (Insulation resistance) : $\geq 1000M\Omega$
- ❑ 耐压 (Withstand voltage) : 800V.Ac/1min
- ❑ 材料 (Material) :
 孔座 (Housing) : 尼龙 (PA66) UL94V-2
 针座 (Wafer) : PBT UL94V-2(0)
 端子 (Terminal) : 磷青铜 (Phos.bronze Tin/plated)




端子 TERMINAL (杜邦 2.0)

型号 Type	适用线规 Applicable wires		电线外径 O.D of wire ins mm	数量 Quantity
	mm ²	AWG#		
HX20011-PT	0.05~0.22	30~24	0.9~1.4	10000PCS/包


HX20011-PT (杜邦 2.0)




HX20011-40AS (杜邦 2.0)




HX20011-40WAS (杜邦 2.0)



HX20011-YS (杜邦 2.0)




HX20011-YSB (杜邦 2.0)



安装尺寸 MOUNTING MEASUREMENT

孔座 HOUSING (杜邦2.0)

线数 Poles	型号 Type	尺寸Dimensions(mm)	
		A	B
4	HX20011-2x2YS	2.0	4.3
6	HX20011-2x3YS	4.0	6.3
8	HX20011-2x4YS	6.0	8.3
10	HX20011-2x5YS	8.0	10.3
12	HX20011-2x6YS	10.0	12.3
14	HX20011-2x7YS	12.0	14.3
16	HX20011-2x8YS	14.0	16.3
18	HX20011-2x9YS	16.0	18.3



线数 Poles	型号 Type	尺寸Dimensions(mm)	
		A	B
20	HX20011-2x10YS	18.0	20.3
22	HX20011-2x11YS	20.0	22.3
24	HX20011-2x12YS	22.0	24.3
26	HX20011-2x13YS	24.0	26.3
28	HX20011-2x14YS	26.0	28.3
30	HX20011-2x15YS	28.0	30.3
...
50	HX20011-2x25YS	48.0	50.3

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Hongxing](#) manufacturer:

Other Similar products are found below :

[0015917161](#) [0022155065](#) [57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-](#)
[4853B](#) [71.350.2428.0](#) [733-134](#) [733-162](#) [760-3052](#) [MHR-64-VUAL](#) [80.063.4001.1](#) [800-90-001-10-001000](#) [801-43-002-10-013000](#)
[801-43-006-10-002000](#) [803-43-024-10-001000](#) [803-93-012-10-001000](#) [8-1437020-4](#) [819-22-004-30-001101](#) [820-22-006-30-001101](#)
[820-22-008-30-001101](#) [821-22-002-10-001101](#)