


技术参数 SPECIFICATIONS


- 线数 (Poles) : 2~15
- 适用线规 (Applicable wires) : AWG28#~24#
- 温度范围 (Temperature range) : -25℃~85℃
- 额定电压 (Voltage rating) : 250V.Ac/Dc
- 额定电流 (Current rating) : 2A
- 接触电阻 (Contact resistance) : $\leq 0.02\Omega$
- 绝缘电阻 (Insulation resistance) : $\geq 1000M\Omega$
- 耐压 (Withstand voltage) : 800V.Ac/1min
- 材料 (Material) :
 - 插头 (Plug housing) : 尼龙 (PA66) UL94V-2(0)
 - 插座 (Receptacle housing) : 尼龙 (PA66) UL94V-2(0)
 - 端子 (Terminal) : 磷青铜 (Phos.bronze Tin/plated)




端子 TERMINAL (20032)

型号 Type	适用线规 Applicable wires mm ² AWG#	电线外径 O.D of wire ins mm	数量 Quantity
HX20032-PT	0.08~0.22 28~24	0.9~1.5	
HX20032-RT	0.08~0.22 28~24	0.9~1.5	

HX20032-PT




HX20032-P




安装尺寸 MOUNTING MEASUREMENT



HX20032-RT



HX20032-R



插头 PLUG HOUSING (20032)

线数 Poles	型号 Type	尺寸 Dimensions(mm)		
		A	B	C
2	HX20032-2P	2.0	6.6	4.6
3	HX20032-3P	4.0	8.6	6.6
4	HX20032-4P	6.0	10.6	8.6
5	HX20032-5P	8.0	12.6	10.6
6	HX20032-6P	10.0	14.6	12.6
7	HX20032-7P	12.0	16.6	14.6
8	HX20032-8P	14.0	18.6	16.6
9	HX20032-9P	16.0	20.6	18.6
10	HX20032-10P	18.0	22.6	20.6
11	HX20032-11P	20.0	24.6	22.6
12	HX20032-12P	22.0	26.6	24.6
13	HX20032-13P	24.0	28.6	26.6
14	HX20032-14P	26.0	30.6	28.6
15	HX20032-15P	28.0	32.6	30.6

插座 RECEPTACLE HOUSING (20032)

线数 Poles	型号 Type	尺寸 Dimensions(mm)		
		A	B	C
2	HX20032-2R	2.0	8.0	4.6
3	HX20032-3R	4.0	10.0	6.6
4	HX20032-4R	6.0	12.0	8.6
5	HX20032-5R	8.0	14.0	10.6
6	HX20032-6R	10.0	16.0	12.6
7	HX20032-7R	12.0	18.0	14.6
8	HX20032-8R	14.0	20.0	16.6
9	HX20032-9R	16.0	22.0	18.6
10	HX20032-10R	18.0	24.0	20.6
11	HX20032-11R	20.0	26.0	22.6
12	HX20032-12R	22.0	28.0	24.6
13	HX20032-13R	24.0	30.0	26.6
14	HX20032-14R	26.0	32.0	28.6
15	HX20032-15R	28.0	34.0	30.6

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Hongxing](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [0009485154](#) [009176003701906](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#) [622-0430](#) [622-3653LF](#)
[63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#) [65781-047](#) [65817-010LF](#) [65817-015LF](#)
[66207-023LF](#) [67016-026LF](#) [67095-007LF](#) [68631-112](#) [68645-018](#) [68648-049](#) [699319-000](#) [70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-](#)
[5020](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [754199-000](#) [760-3052](#) [787-8014-00](#) [FCN-367T-T012/H](#) [80.063.4001.1](#) [800-90-001-](#)
[10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#) [803-43-014-20-001000](#)
[803-43-024-10-001000](#)