


技术参数 SPECIFICATIONS


- 线数 (Poles) : 2~13(30)
- 适用线规 (Applicable wires) : AWG28#~22#
- 适应基板厚度 (Applicable PC board thickness) : 1.6mm
- 温度范围 (Temperature range) : -25℃~85℃
- 额定电压 (Voltage rating) : 250V.Ac/Dc
- 额定电流 (Current rating) : 3A
- 接触电阻 (Contact resistance) : ≤0.02Ω
- 绝缘电阻 (Insulation resistance) : ≥1000MΩ
- 耐压 (Withstand voltage) : 1000V.Ac/1min
- 材料 (Material) :
 孔座 (Housing) : 尼龙 (PA66) UL94V-2(0)
 针座 (Wafer) : 尼龙 (PA66) UL94V-2(0)
 端子 (Terminal) : 磷青铜 (Phos.bronze Tin/plated)




端子 TERMINAL(EH)

型号 Type	适用线规 Applicable wires		电线外径 O.D of wire ins	数量 Quantity
	mm	AWG#	mm	
HX25004-PT	0.08~0.3	28~22	1.0~1.8	8000PCS/盘


HX25004-PT (EH)




HX25004-Y (EH)




HX25005-A (EH)



HX25005-AN (EH)




HX25005-WAP (EH)



HX25005-WAD (EH)



安装尺寸 MOUNTING MEASUREMENT



孔座 HOUSING (EH)

线数 Poles	型号 Type	尺寸 Dimensions(mm)	
		A	B
2	HX25004-2Y	2.5	7.0
3	HX25004-3Y	5.0	9.5
4	HX25004-4Y	7.5	12.0
5	HX25004-5Y	10.0	14.5
6	HX25004-6Y	12.5	17.0
7	HX25004-7Y	15.0	19.5
8	HX25004-8Y	17.5	22.0
9	HX25004-9Y	20.0	24.5
10	HX25004-10Y	22.5	27.0
11	HX25004-11Y	25.0	29.5
12	HX25004-12Y	27.5	32.0
13	HX25004-13Y	30.0	34.5
...
30	HX25004-30Y	72.5	77.0

针座 WAFER (EH)

线数 Poles	型号 Type		尺寸 Dimensions(mm)	
	直式 (180°)	弯式 (90°)	A	B
2	HX25005-2A	HX25005-2WA	2.5	7.5
3	HX25005-3A	HX25005-3WA	5.0	10.0
4	HX25005-4A	HX25005-4WA	7.5	12.5
5	HX25005-5A	HX25005-5WA	10.0	15.0
6	HX25005-6A	HX25005-6WA	12.5	17.5
7	HX25005-7A	HX25005-7WA	15.0	20.0
8	HX25005-8A	HX25005-8WA	17.5	22.5
9	HX25005-9A	HX25005-9WA	20.0	25.0
10	HX25005-10A	HX25005-10WA	22.5	27.5
11	HX25005-11A	HX25005-11WA	25.0	30.0
12	HX25005-12A	HX25005-12WA	27.5	32.5
13	HX25005-13A	HX25005-13WA	30.0	35.0
...
30	HX25005-30A	HX25005-30WA	72.5	77.5

X-ON Electronics

Largest Supplier of Electrical and Electronic Components

Click to view similar products for [Headers & Wire Housings](#) category:

Click to view products by [Hongxing](#) manufacturer:

Other Similar products are found below :

[57102-F02-18ULF](#) [58102-G61-06LF](#) [582553-1](#) [009176003701906](#) [01.001.5753.1](#) [0050291907](#) [02.125.8002.8](#) [609-3404](#) [61062-3](#)
[CSU011177004](#) [622-0430](#) [622-3653LF](#) [63453-116](#) [636-1030](#) [636-1427](#) [636-3427](#) [636-4007](#) [641938-9](#) [65495-038](#) [65692-001LF](#) [65781-018](#)
[65781-047](#) [65817-010LF](#) [65817-015LF](#) [66207-023LF](#) [67095-007LF](#) [67601157](#) [68631-112](#) [68645-018](#) [699319-000](#) [M90C108951C](#)
[70.362.1628.0](#) [70-4210](#) [70-4226B](#) [70-4853B](#) [707-5028](#) [71.350.2428.0](#) [71961-016LF](#) [733-134](#) [733-162](#) [754199-000](#) [760-3052](#) [80.063.4001.1](#)
[800-90-001-10-001000](#) [800-90-010-10-002000](#) [801-43-002-10-013000](#) [801-43-006-10-002000](#) [803-41-018-10-001000](#) [803-43-024-10-](#)
[001000](#) [803-93-012-10-001000](#)